TOSHIBA Transistor Silicon PNP Triple Diffused Type


2SA1923

High Voltage Switching Applications

- High voltage: V_{CEO} = -400 V
- Low saturation voltage: V_{CE} (sat) = -1 V (max) (I_C = -100 mA, I_B = -10 mA)

Maximum Ratings (Ta = 25°C)

Characteristics		Symbol	Rating	Unit	
Collector-base voltage		V _{CBO}	-400	V	
Collector-emitter voltage		V _{CEO}	-400	V	
Emitter-base voltage		V _{EBO}	-7	V	
Collector current	DC	Ι _C	-0.5	A	
	Pulse	I _{CP}	-1		
Base current		I _B	-0.25	А	
Collector power dissipation	Ta = 25°C	D.	1	W	
	Tc = 25°C	PC	10		
Junction temperature		Tj	150	°C	
Storage temperature range		T _{stg}	-55 to 150	°C	




Weight: 0.36 g (typ.)

Unit: mm

Electrical Characteristics (Ta = 25°C)

Chara	acteristics	Symbol	Test Condition	Min	Тур.	Max	Unit
Collector cut-off c	current	I _{CBO}	V _{CB} = -400 V, I _E = 0		—	-10	μA
Emitter cut-off cu	rrent	I _{EBO}	$V_{EB} = -7 V, I_C = 0$		_	-1	μA
Collector-emitter	breakdown voltage	V (BR) CEO	I _C = -10 mA, I _B = 0	-400	_	_	V
DC current gain		h _{FE (1)}	$V_{CE} = -5 V, I_C = -20 mA$	140	_	450	
		h _{FE (2)}	$V_{CE} = -5 V, I_C = -100 mA$	140	_	400	
Collector-emitter	saturation voltage	V _{CE (sat)}	I _C = -100 mA, I _B = -10 mA	_	-0.4	-1.0	V
Base-emitter satu	iration voltage	V _{BE (sat)}	I _C = -100 mA, I _B = -10 mA	_	-0.76	-0.9	V
Transition frequency		f _T	$V_{CE} = -5 V, I_C = -50 mA$	_	35	_	MHz
Collector output capacitance		C _{ob}	$V_{CB} = -10 \text{ V}, \text{ I}_{E} = 0, \text{ f} = 1 \text{ MHz}$	_	18	_	pF
Switching time	Turn-on time	t _{on}	$20 \ \mu s \qquad \text{INPUT} \qquad \downarrow B1 \qquad \text{OUTPUT} \\ \downarrow I_{B2} \qquad \downarrow B2 \qquad \downarrow B2 \qquad \lor V_{CC} = -200 \ V$	_	0.2	_	
	Storage time	t _{stg}		_	2.3	_	μs
	Fall time	t _f	I _{B1} = −10 mA, I _{B2} = 20 mA, DUTY CYCLE ≤ 1%	_	0.2	_	


Marking





Explanation of Lot No.


Month of manufacture: January to December are denoted by letters A to L respectively. Year of manufacture: last decimal digit of the year of manufacture


TOSHIBA














RESTRICTIONS ON PRODUCT USE

- TOSHIBA is continually working to improve the quality and reliability of its products. Nevertheless, semiconductor devices in general can malfunction or fail due to their inherent electrical sensitivity and vulnerability to physical stress. It is the responsibility of the buyer, when utilizing TOSHIBA products, to comply with the standards of safety in making a safe design for the entire system, and to avoid situations in which a malfunction or failure of such TOSHIBA products could cause loss of human life, bodily injury or damage to property.
 In developing your designs, please ensure that TOSHIBA products are used within specified operating ranges as set forth in the most recent TOSHIBA products specifications. Also, please keep in mind the precautions and conditions set forth in the "Handling Guide for Semiconductor Devices," or "TOSHIBA Semiconductor Reliability Handbook" etc..
- The TOSHIBA products listed in this document are intended for usage in general electronics applications (computer, personal equipment, office equipment, measuring equipment, industrial robotics, domestic appliances, etc.). These TOSHIBA products are neither intended nor warranted for usage in equipment that requires extraordinarily high quality and/or reliability or a malfunction or failure of which may cause loss of human life or bodily injury ("Unintended Usage"). Unintended Usage include atomic energy control instruments, airplane or spaceship instruments, transportation instruments, traffic signal instruments, combustion control instruments, medical instruments, all types of safety devices, etc.. Unintended Usage of TOSHIBA products listed in this document shall be made at the customer's own risk.
- The information contained herein is presented only as a guide for the applications of our products. No responsibility is assumed by TOSHIBA CORPORATION for any infringements of intellectual property or other rights of the third parties which may result from its use. No license is granted by implication or otherwise under any intellectual property or other rights of TOSHIBA CORPORATION or others.
- The information contained herein is subject to change without notice.