PAN-SERIES





Features

- (1)Compact and High current density On-board type: Rated current 20A with DC48V input line. (2)Suitable size for the PCB-mounting:
- 46(W) x 12.7(H) x 46(D)mm.
- (3)Matches best for use in conjunction with Densei-Lambda's power modules for telecommunication equipment: Meets EMI-standardized requirements with PAF and/or PAH series used together. (4)Patent and design registration pending.
- Safety standard

Conforms to UL1950, CSA950 and EN60950

Specifications

Item Model		PAN4820
1	Rated voltage (DC)	DC76V
2	Rated current (DC) *	20A
3	Test voltage	Terminal - FG: DC1500V, 1min. Terminal - Terminal: DC100V, 1min.
4	Isolation resistance	Terminal - Case: DC500V, 100Mohm
5	Cooling	Convection cooling or forced air cooling
6	Operating Temperature	$-40 \sim +85^{\circ}$ C (Convection Cooling) $-40 \sim +100^{\circ}$ C (1m/s ² Forced Air Cooling)
7	Operating Humidity	30 ~ 95% RH (No Dewdrop)
8	Storage Temperature	-40 ~ +100°C
9	Storage Humidity	10 ~ 95% RH (No Dewdrop)
10	Vibration	10 ~55Hz Sweep for 1 min Amplitude 0.825mm(max 49.0m/s ²),X,Y,Z, 1 Hour each
11	Weight (typ.)	45g
NOTE		

Convection cooling Ta≦75°C Forced air cooling (1m/sec), Ta≦90°C Refer to derating curve on the right



%

Current



Frequency(MHz)

Frequency (MHz)

173

PAN-SERIES

Connection-1. [Basic Connection]

In input/output of power modules, please connect resistor/capacitor properly as we recommend in our instruction manuals for power modules. Fuse is not included in the unit, so please install appropriate fuse in input side as guided in our instruction manual of power modules.



Quantity of power modules connected / model structure / load condition

- Wiring method of input and output - Surrounding circuits

Connection-2. [Other method of connection] (With baseplate and -V of power module grounded)

This noise filter will provide you with the best performance with the condition of baseplate and output (+V or -V) non-grounded. If baseplate and output (+V or -V) need to be grounded, connect C1, C2, and C3 shown in the above.

