

DATA SHEET

BLV950 UHF push-pull power transistor

Product specification
Supersedes data of 1996 Jan 26

1997 Oct 27

UHF push-pull power transistor

BLV950

FEATURES

- Internal input and output matching for easy matching, high gain and efficiency
- Poly-silicon emitter ballasting resistors for an optimum temperature profile
- Gold metallization ensures excellent reliability.

APPLICATIONS

- Base station transmitters in the 800 to 960 MHz range.

DESCRIPTION

Two NPN silicon planar epitaxial transistors in push-pull configuration, intended for linear common emitter class-AB operation. The transistors are encapsulated in a 4-lead SOT262A2 flange package with 2 ceramic caps. The flange provides the common emitter connection for both transistors.

PINNING - SOT262A2

PIN	SYMBOL	DESCRIPTION
1	c1	collector 1
2	c2	collector 2
3	b1	base 1
4	b2	base 2
5	e	common emitter; connected to flange




Fig.1 Simplified outline and symbol.

QUICK REFERENCE DATA

RF performance at $T_h = 25\text{ }^\circ\text{C}$ in a common emitter push-pull test circuit.

MODE OF OPERATION	f (MHz)	V_{CE} (V)	P_L (W)	G_p (dB)	η_c (%)	d_3 (dBc)
CW, class-AB	900	26	150	≥ 8	≥ 45	-
	960	26	150	≥ 7.5	≥ 45	-
2-tone, class-AB	900	26	150 (PEP)	≥ 8.5	≥ 35	≤ -30
	960	26	150 (PEP)	≥ 8	≥ 35	≤ -30

WARNING

Product and environmental safety - toxic materials

This product contains beryllium oxide. The product is entirely safe provided that the BeO discs are not damaged. All persons who handle, use or dispose of this product should be aware of its nature and of the necessary safety precautions. After use, dispose of as chemical or special waste according to the regulations applying at the location of the user. It must never be thrown out with the general or domestic waste.

UHF push-pull power transistor

BLV950

LIMITING VALUES

In accordance with the Absolute Maximum Rating System (IEC 134).

SYMBOL	PARAMETER	CONDITIONS	MIN.	MAX.	UNIT
Per transistor section					
V_{CBO}	collector-base voltage	open emitter	–	70	V
V_{CEO}	collector-emitter voltage	open base	–	30	V
V_{EBO}	emitter-base voltage	open collector	–	3	V
I_C	collector current (DC)		–	12	A
$I_{C(AV)}$	average collector current		–	12	A
P_{tot}	total power dissipation (DC)	$T_{mb} = 25\text{ °C}$	–	340	W
T_{stg}	storage temperature		–65	+150	°C
T_j	operating junction temperature		–	200	°C

THERMAL CHARACTERISTICS

SYMBOL	PARAMETER	CONDITIONS	MAX.	UNIT
$R_{th\ j-mb}$	thermal resistance from junction to mounting base	$P_{tot} = 340\text{ W}$; $T_{mb} = 25\text{ °C}$; note 1	0.52	K/W
$R_{th\ mb-h}$	thermal resistance from mounting base to heatsink		0.15	K/W

Note

1. Total device; both sections equally loaded; thermal resistance is determined under specified RF operating conditions.

UHF push-pull power transistor

BLV950



CHARACTERISTICS

$T_j = 25\text{ }^\circ\text{C}$ unless otherwise specified.

SYMBOL	PARAMETER	CONDITIONS	MIN.	TYP.	MAX.	UNIT
Per transistor section						
$V_{(BR)CBO}$	collector-base breakdown voltage	open emitter; $I_C = 60\text{ mA}$	70	–	–	V
$V_{(BR)CEO}$	collector-emitter breakdown voltage	open base; $I_C = 150\text{ mA}$	30	–	–	V
$V_{(BR)EBO}$	emitter-base breakdown voltage	open collector; $I_E = 3\text{ mA}$	3	–	–	V
I_{CES}	collector leakage current	$V_{BE} = 0$; $V_{CE} = 28\text{ V}$	–	–	5	mA
h_{FE}	DC current gain	$V_{CE} = 10\text{ V}$; $I_C = 4.5\text{ A}$; note 1	30	–	120	
C_c	collector capacitance	$V_{CB} = 26\text{ V}$; $I_E = i_e = 0$; $f = 1\text{ MHz}$; note 2	–	75	–	pF

Notes

1. Measured under pulse conditions: $t_p \leq 300\text{ }\mu\text{s}$; $\delta \leq 0.01$.
2. Value C_c is that of the die only, it is not measurable because of internal matching network.



UHF push-pull power transistor

BLV950

APPLICATION INFORMATION

RF performance at $T_h = 25\text{ }^\circ\text{C}$ in a common emitter push-pull test circuit; $R_{th\ mb-h} = 0.15\text{ K/W}$.



MODE OF OPERATION	f (MHz)	V _{CE} (V)	I _{CQ} (mA)	P _L (W)	G _p (dB)	η _c (%)	d ₃ (dBc)
CW, class-AB	900	26	2 × 100	150	≥8 typ. 9	≥45 typ. 50	–
	960	26	2 × 100	150	≥7.5 typ. 8.5	≥45 typ. 50	–
2-tone, class-AB	note 1	26	2 × 100	150 (PEP)	≥8.5 typ. 9.5	≥35 typ. 40	≤–28 typ. –31
	note 2	26	2 × 100	150 (PEP)	≥8 typ. 9	≥35 typ. 40	≤–30 typ. –33

Notes

1. $f_1 = 900.0\text{ MHz}$; $f_2 = 900.1\text{ MHz}$.
2. $f_1 = 960.0\text{ MHz}$; $f_2 = 960.1\text{ MHz}$.




Ruggedness in class-AB operation

The BLV950 is capable of withstanding a load mismatch corresponding to $VSWR = 2 : 1$ through all phases under the conditions: $P_L = 150\text{ W}$; $f = 960\text{ MHz}$; $V_{CE} = 26\text{ V}$; $I_{CQ} = 2 \times 100\text{ mA}$; $T_h = 25\text{ }^\circ\text{C}$; $R_{th\ mb-h} = 0.15\text{ K/W}$ and also a load mismatch of $VSWR = 5 : 1$ through all phases at $P_L = 150\text{ W}$ (PEP) and $f_1 = 960.0\text{ MHz}$ and $f_2 = 960.1\text{ MHz}$.



UHF push-pull power transistor

BLV950



UHF push-pull power transistor

BLV950




Fig.9 Class-AB test circuit at 900 to 960 MHz.

UHF push-pull power transistor

BLV950

List of components (see Figs 9 and 10)

COMPONENT	DESCRIPTION	VALUE	DIMENSIONS	CATALOGUE No.
C1, C10	tantalum capacitor	2.2 μ F, 35 V		2022 019 00058
C2, C11, C30, C34, C37, C41	multilayer ceramic chip capacitor; note 1	300 pF, 200 V		
C3, C12	electrolytic capacitor	1 μ F, 63 V		2222 085 78108
C4, C13	electrolytic capacitor	10 μ F, 16 V		2222 085 75109
C5, C14, C31, C40	tantalum capacitor	1 μ F, 35 V		2022 019 00056
C6, C15, C29, C42	multilayer ceramic chip capacitor	100 nF, 50 V		2222 581 76641
C7, C16	multilayer ceramic chip capacitor	10 nF, 50 V		2222 581 76627
C8, C17	multilayer ceramic chip capacitor; note 1	330 pF, 200 V		
C9, C18, C19, C20, C35, C36	multilayer ceramic chip capacitor; note 1	39 pF, 500 V		
C23	multilayer ceramic chip capacitor; note 1	2 pF, 500 V		
C25	multilayer ceramic chip capacitor; note 1	3.9 pF, 500 V		
C21, C22	film dielectric trimmer	9 pF		2222 809 09005
C24, C26	film dielectric trimmer	3.5 pF		2222 809 05215
C27, C28	multilayer ceramic chip capacitor; note 1	68 pF, 500 V		
C32, C39	electrolytic capacitor	10 μ F, 63 V		2222 030 28109
C33, C38	electrolytic capacitor	1 μ F, 63 V		2222 030 38108
L1, L3	stripline; note 2	35 Ω	length 50.7 mm width 4 mm	
L2	semi-rigid cable; note 3	50 Ω	ext. conductor length 50.7 mm ext. diameter 2.2 mm	
L4, L5	stripline; note 2	35 Ω	length 26.5 mm width 4 mm	
L6, L7	stripline; note 2	20 Ω	length 9.2 mm width 8 mm	
L10, L11, L16, L17	stripline; note 2	7 Ω	length 2.5 mm width 27 mm	
L8, L13, L14, L19	grade 4S2 Ferroxcube chip-bead			4330 030 36300
L9, L12	microchoke	4.7 μ H		4322 057 04781
L15, L18	4 turns enamelled 1 mm copper wire	100 nH	int. diameter 6 mm close wound	
L20, L21	stripline; note 2	14 Ω	length 6 mm width 12.5 mm	

UHF push-pull power transistor

BLV950


COMPONENT	DESCRIPTION	VALUE	DIMENSIONS	CATALOGUE No.
L22, L23	stripline; note 2	14 Ω	length 7 mm width 12.5 mm	
L24, L25	stripline; note 2	18 Ω	length 11 mm width 9 mm	
L26, L27	stripline; note 2	50 Ω	length 6.5 mm width 2.5 mm	
L28, L30	stripline; note 2	30 Ω	length 49.3 mm width 5 mm	
L29	semi-rigid cable; note 3	50 Ω	ext. conductor length 49.3 mm ext. diameter 3.6 mm	
R5, R6	metal film resistor	0.4 W, 1 Ω		2322 151 71008
R1, R2	metal film resistor	0.4 W, 5.11 Ω		2322 151 75118
R3, R4	metal resistor	1 W, 5.11 Ω		2322 153 75118

Notes

1. American Technical Ceramics type 100B or capacitor of same quality.
2. The striplines are on a double copper-clad printed-circuit board, with PTFE microfibre-glass dielectric ($\epsilon_r = 2.2$); thickness $\frac{1}{32}$ " ; thickness of the copper sheet $2 \times 35 \mu\text{m}$.
3. Semi-rigid cables soldered respectively on striplines L1 and L28.

UHF push-pull power transistor

BLV950







Dimensions in mm.

The components are situated on one side of the copper-clad PTFE microfibre-glass board, the other side is unetched and serves as a ground plane. Earth connections from the component side to the ground plane are made by through metallization.

Fig.10 Component layout and printed-circuit board for 900 to 960 MHz class-AB test circuit.

UHF push-pull power transistor

BLV950




UHF push-pull power transistor

BLV950

PACKAGE OUTLINE

Flanged double-ended ceramic package; 2 mounting holes; 4 leads

SOT262A2



DIMENSIONS (millimetre dimensions are derived from the original inch dimensions)

UNIT	A	b	c	D	e	E	E ₁	F	H	H ₁	p	Q	q	U ₁	U ₂	w ₁	w ₂	w ₃
mm	5.39 4.62	5.85 5.58	0.16 0.10	21.98 21.71	11.05	10.27 10.05	10.29 10.03	1.78 1.52	20.58 20.06	17.02 16.51	3.28 3.02	2.47 2.20	27.94	34.17 33.90	9.91 9.65	0.51	1.02	0.25
inches	0.212 0.182	0.230 0.220	0.006 0.004	0.865 0.855	0.435	0.404 0.395	0.405 0.396	0.070 0.060	0.81 0.79	0.67 0.65	0.129 0.119	0.097 0.087	1.100	1.345 1.335	0.390 0.380	0.02	0.04	0.01

OUTLINE VERSION	REFERENCES				EUROPEAN PROJECTION	ISSUE DATE
	IEC	JEDEC	EIAJ			
SOT262A2						97-06-28

UHF push-pull power transistor

BLV950

DEFINITIONS

Data Sheet Status	
Objective specification	This data sheet contains target or goal specifications for product development.
Preliminary specification	This data sheet contains preliminary data; supplementary data may be published later.
Product specification	This data sheet contains final product specifications.
Limiting values	
Limiting values given are in accordance with the Absolute Maximum Rating System (IEC 134). Stress above one or more of the limiting values may cause permanent damage to the device. These are stress ratings only and operation of the device at these or at any other conditions above those given in the Characteristics sections of the specification is not implied. Exposure to limiting values for extended periods may affect device reliability.	
Application information	
Where application information is given, it is advisory and does not form part of the specification.	

LIFE SUPPORT APPLICATIONS

These products are not designed for use in life support appliances, devices, or systems where malfunction of these products can reasonably be expected to result in personal injury. Philips customers using or selling these products for use in such applications do so at their own risk and agree to fully indemnify Philips for any damages resulting from such improper use or sale.

UHF push-pull power transistor

BLV950

NOTES

UHF push-pull power transistor

BLV950

NOTES

Philips Semiconductors – a worldwide company

Argentina: see South America

Australia: 34 Waterloo Road, NORTH RYDE, NSW 2113,
Tel. +61 2 9805 4455, Fax. +61 2 9805 4466

Austria: Computerstr. 6, A-1101 WIEN, P.O. Box 213, Tel. +43 160 1010,
Fax. +43 160 101 1210

Belarus: Hotel Minsk Business Center, Bld. 3, r. 1211, Volodarski Str. 6,
220050 MINSK, Tel. +375 172 200 733, Fax. +375 172 200 773

Belgium: see The Netherlands

Brazil: see South America

Bulgaria: Philips Bulgaria Ltd., Energoproject, 15th floor,
51 James Bourchier Blvd., 1407 SOFIA,
Tel. +359 2 689 211, Fax. +359 2 689 102

Canada: PHILIPS SEMICONDUCTORS/COMPONENTS,
Tel. +1 800 234 7381

China/Hong Kong: 501 Hong Kong Industrial Technology Centre,
72 Tat Chee Avenue, Kowloon Tong, HONG KONG,
Tel. +852 2319 7888, Fax. +852 2319 7700

Colombia: see South America

Czech Republic: see Austria

Denmark: Prags Boulevard 80, PB 1919, DK-2300 COPENHAGEN S,
Tel. +45 32 88 2636, Fax. +45 31 57 0044

Finland: Sinikalliontie 3, FIN-02630 ESPOO,
Tel. +358 9 615800, Fax. +358 9 61580920

France: 4 Rue du Port-aux-Vins, BP317, 92156 SURESNES Cedex,
Tel. +33 1 40 99 6161, Fax. +33 1 40 99 6427

Germany: Hammerbrookstraße 69, D-20097 HAMBURG,
Tel. +49 40 23 53 60, Fax. +49 40 23 536 300

Greece: No. 15, 25th March Street, GR 17778 TAVROS/ATHENS,
Tel. +30 1 4894 339/239, Fax. +30 1 4814 240

Hungary: see Austria

India: Philips INDIA Ltd, Band Box Building, 2nd floor,
254-D, Dr. Annie Besant Road, Worli, MUMBAI 400 025,
Tel. +91 22 493 8541, Fax. +91 22 493 0966

Indonesia: see Singapore

Ireland: Newstead, Clonskeagh, DUBLIN 14,
Tel. +353 1 7640 000, Fax. +353 1 7640 200

Israel: RAPAC Electronics, 7 Kehilat Saloniki St, PO Box 18053,
TEL AVIV 61180, Tel. +972 3 645 0444, Fax. +972 3 649 1007

Italy: PHILIPS SEMICONDUCTORS, Piazza IV Novembre 3,
20124 MILANO, Tel. +39 2 6752 2531, Fax. +39 2 6752 2557

Japan: Philips Bldg 13-37, Kohnan 2-chome, Minato-ku, TOKYO 108,
Tel. +81 3 3740 5130, Fax. +81 3 3740 5077

Korea: Philips House, 260-199 Itaewon-dong, Yongsan-ku, SEOUL,
Tel. +82 2 709 1412, Fax. +82 2 709 1415

Malaysia: No. 76 Jalan Universiti, 46200 PETALING JAYA, SELANGOR,
Tel. +60 3 750 5214, Fax. +60 3 757 4880

Mexico: 5900 Gateway East, Suite 200, EL PASO, TEXAS 79905,
Tel. +9-5 800 234 7381

Middle East: see Italy

Netherlands: Postbus 90050, 5600 PB EINDHOVEN, Bldg. VB,
Tel. +31 40 27 82785, Fax. +31 40 27 88399

New Zealand: 2 Wagener Place, C.P.O. Box 1041, AUCKLAND,
Tel. +64 9 849 4160, Fax. +64 9 849 7811

Norway: Box 1, Manglerud 0612, OSLO,
Tel. +47 22 74 8000, Fax. +47 22 74 8341

Philippines: Philips Semiconductors Philippines Inc.,
106 Valero St. Salcedo Village, P.O. Box 2108 MCC, MAKATI,
Metro MANILA, Tel. +63 2 816 6380, Fax. +63 2 817 3474

Poland: Ul. Lukiska 10, PL 04-123 WARSZAWA,
Tel. +48 22 612 2831, Fax. +48 22 612 2327

Portugal: see Spain

Romania: see Italy

Russia: Philips Russia, Ul. Usatcheva 35A, 119048 MOSCOW,
Tel. +7 095 755 6918, Fax. +7 095 755 6919

Singapore: Lorong 1, Toa Payoh, SINGAPORE 1231,
Tel. +65 350 2538, Fax. +65 251 6500

Slovakia: see Austria

Slovenia: see Italy

South Africa: S.A. PHILIPS Pty Ltd., 195-215 Main Road Martindale,
2092 JOHANNESBURG, P.O. Box 7430 Johannesburg 2000,
Tel. +27 11 470 5911, Fax. +27 11 470 5494

South America: Rua do Rocio 220, 5th floor, Suite 51,
04552-903 São Paulo, SÃO PAULO - SP, Brazil,
Tel. +55 11 821 2333, Fax. +55 11 829 1849

Spain: Balmes 22, 08007 BARCELONA,
Tel. +34 3 301 6312, Fax. +34 3 301 4107

Sweden: Kottbygatan 7, Akalla, S-16485 STOCKHOLM,
Tel. +46 8 632 2000, Fax. +46 8 632 2745

Switzerland: Allmendstrasse 140, CH-8027 ZÜRICH,
Tel. +41 1 488 2686, Fax. +41 1 481 7730

Taiwan: Philips Semiconductors, 6F, No. 96, Chien Kuo N. Rd., Sec. 1,
TAIPEI, Taiwan Tel. +886 2 2134 2865, Fax. +886 2 2134 2874

Thailand: PHILIPS ELECTRONICS (THAILAND) Ltd.,
209/2 Sanpavuth-Bangna Road Prakanong, BANGKOK 10260,
Tel. +66 2 745 4090, Fax. +66 2 398 0793

Turkey: Talatpasa Cad. No. 5, 80640 GÜLTEPE/ISTANBUL,
Tel. +90 212 279 2770, Fax. +90 212 282 6707

Ukraine: PHILIPS UKRAINE, 4 Patrice Lumumba str., Building B, Floor 7,
252042 KIEV, Tel. +380 44 264 2776, Fax. +380 44 268 0461

United Kingdom: Philips Semiconductors Ltd., 276 Bath Road, Hayes,
MIDDLESEX UB3 5BX, Tel. +44 181 730 5000, Fax. +44 181 754 8421

United States: 811 East Arques Avenue, SUNNYVALE, CA 94088-3409,
Tel. +1 800 234 7381

Uruguay: see South America

Vietnam: see Singapore

Yugoslavia: PHILIPS, Trg N. Pasica 5/v, 11000 BEOGRAD,
Tel. +381 11 625 344, Fax. +381 11 635 777

For all other countries apply to: Philips Semiconductors, Marketing & Sales Communications,
Building BE-p, P.O. Box 218, 5600 MD EINDHOVEN, The Netherlands, Fax. +31 40 27 24825

Internet: <http://www.semiconductors.philips.com>

© Philips Electronics N.V. 1997

SCA55

All rights are reserved. Reproduction in whole or in part is prohibited without the prior written consent of the copyright owner.

The information presented in this document does not form part of any quotation or contract, is believed to be accurate and reliable and may be changed without notice. No liability will be accepted by the publisher for any consequence of its use. Publication thereof does not convey nor imply any license under patent- or other industrial or intellectual property rights.

Printed in The Netherlands

127067/00/03/pp16

Date of release: 1997 Oct 27

Document order number: 9397 750 02842

Let's make things better.

Philips
Semiconductors



PHILIPS