


7 JVR VARISTOR

Part Number	Maximum Allowable Voltage		Varistor Voltage V@0.1mA		Maximum Clamping Voltage V@ 5A (V)	Withstanding Surge Current		Rated Wattage (W)	Energy 10/1000 s (J)	UL	CSA	VDE
	ACrms (V)	DC (V)	Tolerance Range (V)	1Time (A)		2 Times (A)						
JVR07S180M65□△△	11	14	18	+ 20%	•36	500	250	0.02	1.5	✓		✓
JVR07S220L 65□△△	14	18	22	+ 15%	• 43				1.7	✓		✓
JVR07S270K65□△△	17	22	27		• 53				2.1	✓		✓
JVR07S330K65□△△	20	26	33		• 65				2.8	✓		✓
JVR07S390K65□△△	25	31	39		• 77				3.0	✓		✓
JVR07S470K65□△△	30	38	47		• 93				3.8	✓		✓
JVR07S560K65□△△	35	45	56		• 110				4.4	✓		✓
JVR07S680K65□△△	40	56	68		• 135				5.4	✓		✓
JVR07S820K65□△△	50	65	82		135				7.0	✓		✓
JVR07S101K65□△△	60	85	100	+10%	165				1750	1250	0.25	9.0
JVR07S121K65□△△	75	100	120		200	11.0	✓					✓
JVR07S151K65□△△	95	125	150		250	13.0	✓					✓
JVR07S181K65□△△	115	150	180		300	16.0	✓					✓
JVR07S201K65□△△	130	170	200		340	17.5	✓	✓				✓
JVR07S221K65□△△	140	180	220		360	19.0	✓	✓				✓
JVR07S241K65□△△	150	200	240		395	21.0	✓	✓				✓
JVR07S271K65□△△	175	225	270		455	24.0	✓	✓				✓
JVR07S301K65□△△	195	250	300		505	26.0	✓	✓				✓
JVR07S331K65□△△	210	275	330		550	28.0	✓	✓				✓
JVR07S361K65□△△	230	300	360		595	32.0	✓	✓				✓
JVR07S391K65□△△	250	320	390		650	35.0	✓	✓				✓
JVR07S431K65□△△	275	350	430		710	40.0	✓	✓				✓
JVR07S471K65□△△	300	385	470		775	42.0	✓	✓				✓
JVR07S511K65□△△	320	418	510		842	45.0	✓	✓				✓
JVR07S561K65□△△	350	460	560		920	51.0	✓	✓				✓
JVR07S621K65□△△	385	505	620		1025	54.0	✓	✓				✓
JVR07S681K65□△△	420	560	680		1120	56.0	✓	✓				✓
JVR07S751K65□△△	460	615	750		1240	58.0	✓	✓				✓
JVR07S781K65□△△	485	640	780		1290	59.0	✓	✓				✓
JVR07S821K65□△△	510	670	820	1355	60.0	✓	✓	✓				

1) The clamping voltage from 180M to 680K are tested with current 2.5A.
For application required ratings not shown, contact RFE application engineering.

- : Lead Style
- Y: vertical kink (standard)
- P: straight leads
- △△ : Lead Length / Packing Method



PULSE RATING CURVES

