

MPC8641 and MPC8641D Integrated Host Processor Hardware Specifications Addendum for the MC8641xTxxnnnxC Series

This document describes part-number-specific changes to recommended operating conditions and revised electrical specifications, as applicable, from those described in the general *MPC8641 and MPC8641D Integrated Host Processor Hardware Specifications* (Document No. MPC8641DEC).

Specifications provided in this document supersede those in the *MPC8641 and MPC8641D Integrated Host Processor Hardware Specifications*, Rev. 1 or later, for the part numbers listed in [Table A](#) only. Specifications not addressed herein are unchanged.

Because this document is frequently updated, refer to the website listed on the back page of this document or contact your Freescale sales office for the latest version.

Note that headings and table numbers in this document are not consecutively numbered. They are intended to correspond to the heading or table affected in the general hardware specification.

Freescale Part Numbers Affected:

MC8641DTHX1333JC
MC8641DTHX1250HC
MC8641DTHX1000NC
MC8641DTHX1000GC
MC8641THX1333JC
MC8641THX1250HC
MC8641THX1000NC
MC8641THX1000GC
MC8641DTVU1333JC
MC8641DTVU1250HC
MC8641DTVU1000NC
MC8641DTVU1000GC
MC8641TVU1333JC
MC8641TVU1250HC
MC8641TVU1000NC
MC8641TVU1000GC

Part numbers addressed in this document are listed in [Table A](#).

Table A. Part Numbers Addressed by This Data Sheet

| Freescale Part Number | Operating Conditions | | | Significant Differences from Hardware Specification |
|-----------------------|----------------------|----------------------|---------------------|---|
| | CPU Frequency (MHz) | V _{DD-Core} | T _j (°C) | |
| MC8641DTHX1333JC | 1333 | 1.05 V ± 50 mV | -40 to 105 | Modified JTAG AC timing; extended junction temperature range. |
| MC8641DTHX1250HC | 1250 | 1.05 V ± 50 mV | | |
| MC8641DTHX1000NC | 1000 | 0.95 V ± 50 mV | | |
| MC8641DTHX1000GC | 1000 | 1.05 V ± 50 mV | | |
| MC8641THX1333JC | 1333 | 1.05 V ± 50 mV | | |
| MC8641THX1250HC | 1250 | 1.05 V ± 50 mV | | |
| MC8641THX1000NC | 1000 | 0.95 V ± 50 mV | | |
| MC8641THX1000GC | 1000 | 1.05 V ± 50 mV | | |
| MC8641DTVU1333JC | 1333 | 1.05 V ± 50 mV | | |
| MC8641DTVU1250HC | 1250 | 1.05 V ± 50 mV | | |
| MC8641DTVU1000NC | 1000 | 0.95 V ± 50 mV | | |
| MC8641DTVU1000GC | 1000 | 1.05 V ± 50 mV | | |
| MC8641TVU1333JC | 1333 | 1.05 V ± 50 mV | | |
| MC8641TVU1250HC | 1250 | 1.05 V ± 50 mV | | |
| MC8641TVU1000NC | 1000 | 0.95 V ± 50 mV | | |
| MC8641TVU1000GC | 1000 | 1.05 V ± 50 mV | | |

2 General Parameters

This section summarizes changes to the general parameters of the MPC8641 described in the *MPC8641 and MPC8641D Integrated Host Processor Hardware Specifications*.

- Modified JTAG AC timing
 - t_{JTDVKH} (min) = 15 ns
- Extended junction temperature range
 - T_J = -40 to 105 °C

2.1 Overall DC Electrical Characteristics

2.1.2 Recommended Operating Conditions

Table 2 provides the recommended operating conditions for the MPC8641 part numbers described herein.

Table 2. Recommended Operating Conditions

| Characteristic | Symbol | Recommended Value | Unit | Notes |
|----------------------------|--------|-------------------|------|-------|
| Junction temperature range | T_J | -40 to 105 | °C | — |

11.2 JTAG AC Electrical Specifications

Table 44 provides the JTAG AC timing specifications for the MPC8641 part numbers described herein.

Table 44. JTAG AC Timing Specifications (Independent of SYSCLK) ¹

| Parameter | Symbol ² | Min | Max | Unit | Notes |
|--------------------------------|------------------------------|---------|--------|------|-------|
| Input setup times: | | | | ns | |
| Boundary-scan data TMS, TDI | t_{JTDVKH} t_{JTIVKH} | 15 0 | — — | | 4 |

Notes:

- All outputs are measured from the midpoint voltage of the falling/rising edge of t_{TCLK} to the midpoint of the signal in question. The output timings are measured at the pins. All output timings assume a purely resistive 50- Ω load (see Figure 32). Time-of-flight delays must be added for trace lengths, vias, and connectors in the system.
- The symbols used for timing specifications herein follow the pattern of $t_{(first\ two\ letters\ of\ functional\ block)(signal)(state)\ (reference)(state)}$ for inputs and $t_{(first\ two\ letters\ of\ functional\ block)(reference)(state)(signal)(state)}$ for outputs. For example, t_{JTDVKH} symbolizes JTAG device timing (JT) with respect to the time data input signals (D) reaching the valid state (V) relative to the t_{JTG} clock reference (K) going to the high (H) state or setup time. Also, t_{JTDXKH} symbolizes JTAG timing (JT) with respect to the time data input signals (D) went invalid (X) relative to the t_{JTG} clock reference (K) going to the high (H) state. Note that, in general, the clock reference symbol representation is based on three letters representing the clock of a particular functional. For rise and fall times, the latter convention is used with the appropriate letter: R (rise) or F (fall).
- Non-JTAG signal input timing with respect to t_{TCLK} .

21 Ordering Information

21.1 Part Numbers Fully Addressed by This Document

Table 74 provides the ordering information for the MPC8641 parts described in this document.

Table 74. Part Numbering Nomenclature

| MC | nnnn | x | w | xx | nnnn | x | x |
|--------------|-----------------|--------------------------------------|-------------------|---|---|---|---|
| Product Code | Part Identifier | Core Count | Temp | Package ¹ | Core Processor Frequency ² (MHz) | DDR speed (MHz) | Product Revision Level |
| MC | 8641 | Blank = Single Core D = Dual Core | T = -40 to 105 °C | HX = High-lead HCTE FC-CBGA VU = RoHS lead-free HCTE FC-CBGA | 1000, 1250, 1333 | N = 500 MHz ⁴ J = 533 MHz H = 500 MHz G = 400 MHz | Revision C = 2.1 System Version Register Value for Rev C: 0x8090_0021 - MPC8641 0x8090_0121 - MPC8641D |

Notes:

1. See Section 16, "Package," for more information on available package types.
2. Processor core frequencies supported by parts addressed by this specification only. Not all parts described in this specification support all core frequencies. Additionally, parts addressed by part number specifications may support other maximum core frequencies.
3. The P prefix in a Freescale part number designates a "Pilot Production Prototype" as defined by Freescale SOP 3-13. These parts have only preliminary reliability and characterization data. Before pilot production prototypes may be shipped, written authorization from the customer must be on file in the applicable sales office acknowledging the qualification status and the fact that product changes may still occur while shipping pilot production prototypes.
4. Part Number MC8641xwxx1000NX is our low V_{DD_Core} device. $V_{DD_Core} = 0.95\text{ V}$ and $V_{DD_PLAT} = 1.05\text{ V}$.

Document Revision History

Table B provides a revision history for this hardware specification addendum.

Table B. Document Revision History

| Rev. Number | Date | Substantive Change(s) |
|-------------|---------|-----------------------|
| 0 | 12/2008 | Initial release. |

THIS PAGE INTENTIONALLY LEFT BLANK

THIS PAGE INTENTIONALLY LEFT BLANK

THIS PAGE INTENTIONALLY LEFT BLANK

How to Reach Us:

Home Page:

www.freescale.com

Web Support:

<http://www.freescale.com/support>

USA/Europe or Locations Not Listed:

Freescale Semiconductor, Inc.
Technical Information Center, EL516
2100 East Elliot Road
Tempe, Arizona 85284
1-800-521-6274 or
+1-480-768-2130
www.freescale.com/support

Europe, Middle East, and Africa:

Freescale Halbleiter Deutschland GmbH
Technical Information Center
Schatzbogen 7
81829 Muenchen, Germany
+44 1296 380 456 (English)
+46 8 52200080 (English)
+49 89 92103 559 (German)
+33 1 69 35 48 48 (French)
www.freescale.com/support

Japan:

Freescale Semiconductor Japan Ltd.
Headquarters
ARCO Tower 15F
1-8-1, Shimo-Meguro, Meguro-ku
Tokyo 153-0064
Japan
0120 191014 or
+81 3 5437 9125
support.japan@freescale.com

Asia/Pacific:

Freescale Semiconductor China Ltd.
Exchange Building 23F
No. 118 Jianguo Road
Chaoyang District
Beijing 100022
China
+86 10 5879 8000
support.asia@freescale.com

For Literature Requests Only:

Freescale Semiconductor
Literature Distribution Center
P.O. Box 5405
Denver, Colorado 80217
1-800 441-2447 or
+1-303-675-2140
Fax: +1-303-675-2150
LDCForFreescaleSemiconductor@hibbertgroup.com

Information in this document is provided solely to enable system and software implementers to use Freescale Semiconductor products. There are no express or implied copyright licenses granted hereunder to design or fabricate any integrated circuits or integrated circuits based on the information in this document.

Freescale Semiconductor reserves the right to make changes without further notice to any products herein. Freescale Semiconductor makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does Freescale Semiconductor assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation consequential or incidental damages. "Typical" parameters which may be provided in Freescale Semiconductor data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. Freescale Semiconductor does not convey any license under its patent rights nor the rights of others. Freescale Semiconductor products are not designed, intended, or authorized for use as components in systems intended for surgical implant into the body, or other applications intended to support or sustain life, or for any other application in which the failure of the Freescale Semiconductor product could create a situation where personal injury or death may occur. Should Buyer purchase or use Freescale Semiconductor products for any such unintended or unauthorized application, Buyer shall indemnify and hold Freescale Semiconductor and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that Freescale Semiconductor was negligent regarding the design or manufacture of the part.

Freescale are trademarks or registered trademarks of Freescale Semiconductor, Inc. in the U.S. and other countries. All other product or service names are the property of their respective owners. The Power Architecture and Power.org word marks and the Power and Power.org logos and related marks are trademarks and service marks licensed by Power.org.

© Freescale Semiconductor, Inc., 2008. All rights reserved.

Document Number: MPC8641DECS01AD

Rev. 0
12/2008

