

Voice Switched Speakerphone Circuit with Speaker Amplifier

■ GENERAL DESCRIPTION

The NJW1128 is a Voice Switched Speakerphone Circuit. It includes all of functions processing a high quality hands-free speakerphone system, such as the necessary amplifiers (Mic , Receive ,Line, Speaker), attenuators, level detectors functions.

The NJW1128 is controllable independently power-down of the speaker amplifier and the entire IC excluding the speaker amplifier.

All external capacitors are sufficient small so that ceramic capacitors are applied.

■ PACKAGE OUTLINE



NJW1128FR3

■ APPLICATION


- Video Door Phone
- Conference System
- Wireless Application
- Security System

■ FEATURES

- Operating voltage range 3.9 to 5.5V
- Attenuator gain range between Transmit and Receive 52dB
- Speaker amplifier
- Microphone amplifier with mute function
- Force to Receive, Transmit, or Idle modes
- Mode -watching monitor
- Background noise monitor for each path
- 4-point signal sensing
- Chip disable Pin powers down the entire IC excluding the speaker amplifier
- Speaker switch Pin power down the speaker amplifier
- Microphone and Receive Amplifiers pinned out for flexibility
- Package Outline

LQFP48-R3

■ BLOCK DIAGRAM



NJW1128

■ ABSOLUTE MAXIMUM RATING (Ta=25°C)

| PARAMETER | SYMBOL | RATING | UNIT |
|-----------------------------|-------------------|----------------------------|------|
| Power Supply Voltage | V ₊ | 7 | V |
| Power Dissipation | P _D | 1,330(Note1) | mW |
| Operating Temperature Range | T _{opr} | -40 ~ +85 | °C |
| Storage Temperature Range | T _{stg} | -40 ~ +125 | °C |
| Maximum Input Voltage | V _{IMAX} | 0 ~ V ⁺ (Note2) | V |

(Note1) EIA/JEDEC STANDARD Test board (76.2x114.3x1.6mm, 2layer, FR-4) mounting

■ OPERATING VOLTAGE

| PARAMETER | SYMBOL | TEST CONDITION | MIN. | TYP. | MAX. | UNIT |
|-------------------|----------------|----------------|------|------|------|------|
| Operating Voltage | V ⁺ | - | 3.9 | 5.0 | 5.5 | V |

■ ELECTRICAL CHARACTERISTICS (Ta=25°C, V⁺=5V, Vin=150mVrms/1kHz, MUT=CD=SPSW= V⁺, MON=OPEN, R_{VLC}=0Ω)

• Power Supply

| PARAMETER | SYMBOL | TEST CONDITION | MIN. | TYP. | MAX. | UNIT |
|---------------------|------------------|--------------------------|------|------|------|------|
| Operating Current 1 | I _{CC1} | RX-mode (Receive) | 2.0 | 3.5 | 6.0 | mA |
| Operating Current 2 | I _{CC2} | TX-mode (Transmit) | 2.0 | 3.5 | 6.0 | mA |
| Operating Current 3 | I _{CC3} | Idle-mode (Standby) | 2.0 | 3.5 | 6.0 | mA |
| Operating Current 4 | I _{CC4} | Idle-mode ,SPSW=PD | 1.0 | 2.5 | 4.0 | mA |
| Operating Current 5 | I _{CC5} | Idle-mode ,CD=PD,SPSW=PD | 0.5 | 1 | 1.5 | mA |
| Reference Voltage | V _{REF} | No signal,Idle-mode | 2.2 | 2.5 | 2.8 | V |

• Receive Attenuator(RxIN=200Vrms,Receive Amplifier Gv=0dB)

| PARAMETER | SYMBOL | TEST CONDITION | MIN. | TYP. | MAX. | UNIT |
|---------------------------|------------------|------------------------------------|------|------|------|------|
| Receive Attenuator Gain 1 | G _{R1} | RX-mode (Receive) | 3.0 | 6.0 | 9.0 | dB |
| Receive Attenuator Gain 2 | G _{R2} | TX-mode (Transmit) | -42 | -46 | -50 | dB |
| Receive Attenuator Gain 3 | G _{R3} | Idle-mode (Standby) | -17 | -20 | -23 | dB |
| Range R to T mode | dG _R | RX-mode – TX-mode | 47 | 52 | 57 | dB |
| Dynamic DC offset | G _{RDC} | RX-mode – TX-mode (DC) | -50 | - | 50 | mV |
| Volume control range | G _{RVR} | RX-mode,R _{VLC} =0Ω-100kΩ | 35 | 45 | 55 | dB |

• Transmit Attenuator (TxIN=200Vrms,Mic.amplifier Gv=0dB)

| PARAMETER | SYMBOL | TEST CONDITION | MIN. | TYP. | MAX. | UNIT |
|----------------------------|------------------|------------------------|------|------|------|------|
| Transmit Attenuator Gain 1 | G _{T1} | TX-mode (Transmit) | 3.0 | 6.0 | 9.0 | dB |
| Transmit Attenuator Gain 2 | G _{T2} | RX-mode (Receive) | -42 | -46 | -50 | dB |
| Transmit Attenuator Gain 3 | G _{T3} | Idle-mode (Standby) | -17 | -20 | -23 | dB |
| Range R to T mode | dG _T | TX-mode – RX-mode | 47 | 52 | 57 | dB |
| Dynamic DC offset | G _{TDC} | TX-mode – RX-mode (DC) | -50 | - | 50 | mV |

•MIC Amplifier(TxIN=1mVrms,Gv=40dB,R_L=5.1kΩ)

| PARAMETER | SYMBOL | TEST CONDITION | MIN. | TYP. | MAX. | UNIT |
|------------------------|--------------------|----------------|------|------|------|------|
| Output Offset Voltage | V _{MOS} | RF=300kΩ | -50 | 0.0 | 50 | mV |
| Input Bias Current | I _{MBIAS} | | - | 30 | - | nA |
| Voltage Gain 1 | G _{VM1} | f=1kHz | - | 40 | - | dB |
| Voltage Gain 2 | G _{VM2} | f=20kHz | - | 36 | - | dB |
| Maximum Output Voltage | V _{MMAX} | THD=1% | 1.0 | - | - | Vrms |
| Maximum Attenuation | G _{MMUTE} | MUT=MUTE | -70 | -73 | - | dB |

•Receive Amplifier (RxIN=1mVrms,Gv=40dB,R_L=5.1kΩ)

| PARAMETER | SYMBOL | TEST CONDITION | MIN. | TYP. | MAX. | UNIT |
|------------------------|--------------------|----------------|------|------|------|------|
| Output Offset Voltage | V _{ROS} | RF=300kΩ | -50 | 0.0 | 50 | mV |
| Input Bias Current | I _{RBIAS} | | - | 30 | - | nA |
| Voltage Gain 1 | G _{VR1} | f=1kHz | - | 40 | - | dB |
| Voltage Gain 2 | G _{VR2} | f=20kHz | - | 36 | - | dB |
| Maximum Output Voltage | V _{RMAX} | THD=1% | 1.0 | - | - | Vrms |

•Line Amplifier (LINEIN=50mVrms, Gv=26dB,R_L=1.2kΩ)

| PARAMETER | SYMBOL | TEST CONDITION | MIN. | TYP. | MAX. | UNIT |
|---------------------------|--------------------|---------------------------------|------|------|------|------|
| Output Offset Voltage | V _{LOS} | RF=51kΩ | -50 | 0.0 | 50 | mV |
| Input Bias Current | I _{RBIAS} | | - | 30 | - | nA |
| Voltage Gain 1 | G _{VL1} | f=1kHz | - | 26 | - | nA |
| Voltage Gain 2 | G _{VL2} | f=20kHz | - | 25 | - | nA |
| Gain Bandwidth | G _{LBW} | RL=600Ω,LIO | - | 1.5 | - | MHz |
| Closed Loop Gain | G _{LC} | RL=1.2kΩ,LIO- to LIO+ | -0.5 | 0 | 0.5 | dB |
| Maximum Output Voltage | V _{LMAX} | RL=1.2kΩ,THD=1% | 2.0 | - | - | Vrms |
| Total Harmonic Distortion | THD _{LN} | VIN=100mVrms,Gv=20dB RL=1.2Ω | - | - | 0.5 | % |

•Speaker Amplifier (SPIN=50mVrms, Gv=26dB,R_L=32Ω)

| PARAMETER | SYMBOL | TEST CONDITION | MIN. | TYP. | MAX. | UNIT |
|---------------------------|---------------------|--|------|------|------|------|
| Output Offset Voltage | V _{SPOS} | RF=51kΩ | -50 | 0.0 | 50 | mV |
| Voltage Gain 1 | G _{VSP1} | f=1kHz | - | 26 | - | dB |
| Voltage Gain 2 | G _{VSP2} | f=20kHz | - | 24 | - | dB |
| Voltage Gain 3 | G _{VSP3} | f=1kHz, G _{VSP} =6dB,RL=8Ω | - | 6 | - | dB |
| Voltage Gain 4 | G _{VSO4} | f=20kHz, G _{VSP} =6dB,RL=8Ω | - | 4 | - | dB |
| Closed Loop Gain | G _{LC} | SPO- to SPO+ | -0.6 | 0 | 0.6 | dB |
| Maximum Output Power | P _O MAX1 | RL=32Ω,THD=3% | 200 | 300 | - | mW |
| | P _O MAX2 | RL=8Ω,THD=3% | 300 | 500 | - | mW |
| Total Harmonic Distortion | THD _{SP1} | VIN=500mVrms,f=1KHz, RL=32Ω,G _{VD} =26dB | | - | 1.0 | % |
| | THD _{SP2} | VIN=500mVrms,f=1KHz, RL=8Ω,G _{VD} =6dB | - | - | 1.0 | % |

NJW1128

•MONITOR TERMINAL (32Pin)

| PARAMETER | SYMBOL | TEST CONDITION | MIN. | TYP. | MAX. | UNIT |
|------------------------|------------------|-------------------|---------------------|------|----------------|------|
| R _X -mode | Rx | - | V ⁺ -0.6 | - | V ⁺ | V |
| T _x -mode | Tx | - | GND | - | 0.6 | V |
| Idle-mode | Idle | No Signal | 2.4 | 2.5 | 2.6 | V |
| Maximum Output Current | I _{MON} | Rx-mode / Tx-mode | - | 0.9 | - | mA |

■ CONTROL CHARACTERISTICS (MUT)

| PARAMETER | SYMBOL | TEST CONDITION | MIN. | TYP. | MAX. | UNIT |
|--------------------------|------------------|----------------|------|------|------|------|
| Low Level Input Voltage | V _{IL1} | - | - | - | 0.3 | V |
| High Level Input Voltage | V _{IH1} | - | 1.5 | - | - | V |

■ CONTROL CHARACTERISTICS (RTSW)

| PARAMETER | SYMBOL | TEST CONDITION | MIN. | TYP. | MAX. | UNIT |
|--------------------------|------------------|----------------|---------------------|------|------|------|
| Low Level Input Voltage | V _{IL2} | - | - | - | 0.3 | V |
| High Level Input Voltage | V _{IH2} | - | V ⁺ -0.3 | - | - | V |

■ FUNCTION

•CD

| INPUT VOLTAGE | STATUS | OPERATION |
|-----------------|--------|---|
| V _{IH} | ACTIVE | NJW1128 is active. |
| V _{IL} | MUTE | NJW1128 is stand-by except Speaker Amplifier. |

•MUT

| INPUT VOLTAGE | STATUS | OPERATION |
|-----------------|--------|---------------------------------|
| V _{IH} | MUTE | The microphone input is mute. |
| V _{IL} | ACTIVE | The microphone input is active. |

•SPSW

| INPUT VOLTAGE | STATUS | OPERATION |
|-----------------|--------|------------------------------------|
| V _{IH} | ACTIVE | The Speaker Amplifier is Active. |
| V _{IL} | PD | The Speaker Amplifier is Stand-by. |


•RTSW

| INPUT VOLTAGE | STATUS | OPERATION |
|-----------------|----------|--|
| V _{IH} | Receive | Force to Receive mode. |
| OPEN | AUTO | Receive mode and Transmit mode are automatically switched. |
| V _{IL} | Transmit | Force to Transmit mode. |







•R_{VLC} (26pin)

| IMPEDANCE | STATUS | OPERATION |
|-----------|--------------------|---|
| 0 | Vol _{MAM} | The Receive attenuator Volume is maximum. |
| 100kΩ | Vol _{MIN} | The Receive attenuator Volume is minimum. |







■ APPLICATION CIRCUIT









■ TYPICAL CHARACTERISTICS








■ TYPICAL CHARACTERISTICS



■ TYPICAL CHARACTERISTICS




■ TYPICAL CHARACTERISTICS




■ TYPICAL CHARACTERISTICS


Rx Att Maximum Output Voltage vs Load Impedance
V+=5.0V , Ta=25degC




Tx Att Maximum Output Voltage vs Load Impedance
V+=5.0V , Ta=25degC








Line Amp Maximum Output Voltage vs Load Impedance
V+ = 5.0V , Rf = 51k Ω , Ta=25degC








Monitor out Maximum Output Voltage vs Load Impedance
V+=5.0V , Ta=25degC





■ TYPICAL CHARACTERISTICS



■ TYPICAL CHARACTERISTICS



■ TYPICAL CHARACTERISTICS



[CAUTION]

The specifications on this databook are only given for information, without any guarantee as regards either mistakes or omissions. The application circuits in this databook are described only to show representative usages of the product and not intended for the guarantee or permission of any right including the industrial rights.