

6 – 18 GHz 28 dBm Amplifier

FEATURES

- P₁ dB: 28 dBm
- Noise Figure: 3.5 dB
- Bias Condition: 1400 mA @ 12 V
- Small Signal Gain: 30 dB



DESCRIPTION

The TA060-180-30-28 is a 28 dBm amplifier designed for high linear application in the 6 to 18 GHz frequency range. This amplifier utilizes high power devices that provide high gain and wide dynamic range. High efficiency operation is achieved by using hybrid MIC designs and advanced GaAs PHEMT devices. The amplifier requires only a +12V DC power supply.

ELECTRICAL SPECIFICATIONS at 25 ° C

Symbol	Description	Min.	Typ.	Max.	Unit
FREQ	Frequency Range	6		18	GHz
SSG	Small Signal Gain	30*			dB
GOF	Small Signal Gain Flatness		± 1	± 1.25	dB
P ₁ dB	Output Power at 1 dB Gain Compression	28	28.5		dBm
NF	Noise Figure		3.5	4.0	dB
VSWR, IN	Input VSWR		1.8:1	2:1	dB
VSWR, OUT	Output VSWR		1.8:1	2:1	dB
VDC	DC Supply Voltage (with built-in regulator)		12		Volt
IDC	Current Supply		1.3	1.4	A
OTR	Operating Temperature Range	-30		60	°C

* Actual gain and current depend on configuration.

CASE: HD7

Note: The previous product part number of TA060-180-30-28 is TC6031K.