

Xeon 5 Power White LED

OSXXX2E5D1E

VER C.2


■ Features


- Highest Luminous Flux
- Super Energy Efficiency
- Long Lifetime Operation
- Superior ESD protection
- Superior UV Resistance

■ Applications

- Read lights (car, bus, aircraft)
- Portable (flashlight, bicycle)
- Bollards / Security / Garden
- Traffic signaling / Beacons
- In door / Out door Commercial lights
- Automotive Ext

Anode(+)








Unit:mm Tolerance:±0.30mm

■ Absolute Maximum Rating

(Ta=25)

Itam	Crumb of	Value	Unit	
Item	Symbol	White/ Warm white		
DC Forward Current	I_{F}	800	mA	
Pulse Forward Current*	I_{FP}	1000	mA	
Reverse Voltage	V_R	10	V	
Power Dissipation	P_{D}	7200	mW	
Operating Temperature	Topr	- 30 ∼ +85		
Storage Temperature	Tstg	-40~ +100		
Lead Soldering Temperature	Tsol	260 /5sec		

■Directivity



■ Electrical -Optical Characteristics (Ta=25)

- ====================================			30200	7.~	<u> </u>									
Part Number	Color		$V_{F}(V)$		$I_R(\mu A)$	CCT	Luminous Flux		λD(nm)		2θ1/2			
							(K)	v (lm)					(deg)	
			Min.	Тур.	Max.	Max.	Тур	Min	Тур.	Max.	Min.	Тур.	Max.	
			I _F =700mA		$V_R=10V$	I _F =700mA								
OSW4X2E5D1E	Pure White	W4	6.5	7.0	9.0	10	6500	300	320	-	X=0	31 ,Y=0.33		125
OSM5X2E5D1E	Warm White	M5	6.5	7.0	9.0	10	3000	280	300	-	X=0.	44,Y=0.41		

Note: Don't drive at rated current more than 5s without heat sink for Xeon 5 emitter series.

LED & Application Technologies











http://www.optosupply.com VER A.0

^{*}Pulse width Max.10ms Duty ratio max 1/10



Xeon 5 Power White LED

OSXXX2E5D1E

VER C.2

■ Handling of Silicone Lens LEDs

Notes for handling of silicone lens LEDs

- Please do not use a force of over 3kgf impact or pressure on the silicone lens, otherwise it will cause a catastrophic failure.
- The LEDs should only be picked up by making contact with the sides of the LED body.
- Avoid touching the silicone lens especially by sharp tools such as Tweezers.
- Avoid leaving fingerprints on the silicone lens.
- Please store the LEDs away from dusty areas or seal the product against dust.
- When populating boards in SMT production, there are basically no restrictions regarding the form of the pick and place nozzle, except that mechanical pressure on the silicone lens must be prevented.
- Please do not mold over the silicone lens with another resin. (epoxy, urethane, etc)



