

# □ MN103SH6 Series

Type	MN103SFH6K
Internal ROM type	FLASH
ROM (byte)	256K
RAM (byte)	12K
Package (Lead-free)	UBGA128-P-0707AE
Minimum Instruction Execution Time	25 ns (2.2 V to 5.5 V)

## ■ Interrupts

8 external interrupts

68 internal interrupts: Watchdog timer. Timer. 16-bit timer expansion PWM finish. Serial I/F. A/D conversion finish. DMA. System error

## ■ Timer Counter

8-bit timer × 8

Timer 0 to 7 .....Interval timer. Event count. Cascading connectable (Usable as 16-bit, 24-bit and 32-bit counter)

16-bit timer × 8

Timer C0 to C5 .....Interval timer. Event count. Input capture. PWM output (Cycle and pulse width variable)

Timer C6, C7 .....Interval timer. Event count. Input capture. PWM output (Cycle and pulse width variable). Expansion PWM output

## ■ Serial interface

Multi-master I<sup>2</sup>C/Synchronous interface selective × 2

UART (full duplex) /Synchronous interfaces selective × 3

## ■ DMA controller

Number of channels: 4 channels

## ■ I/O Pins

I/O 82 : Common use × 82

## ■ A/D converter

(10-bit resolution 9 channels) × 2 unit

Minimum conversion time: 1.3 μs

Simultaneous conversion of 2 unit are available

Conversion start synchronized with timer 1, 3, C0, C1 or PWM for motor automatic control (PID) are available

## ■ D/A converter

(8-bit resolution 1 channel) × 6 unit

## ■ Motor Control PWM

PWM for motor automatic control (PID) × 3

PID operation and motor control PWM output (operation parameter and PWM parameter adjustments possible)

## ■ Electrical Characteristics (A/D converter characteristics)

Parameter	Symbol	Condition	Limit			Unit
			min	typ	max	
Non-linear error		VDD5 = 5.0 V. VSS = 0 V			±3	LSB
Differential non-linearity error		Vref+ = 5.0 V. TAD = 100 ns			±3	LSB
A/D conversion time			1.3			μs
Analog input voltage			VSS		Vref+	V

■ Pin Assignment  
UBGA128-P-0707AE

	A	B	C	D	E	F	G	H	J	K	L	M	
12	N.C.	N.C.	P62, TMC4BIO	P60, TMC3BIO IRQ7	P56, TMC2BIO	PA1, IRQ6	P53, TMC7EP3, TMC7DIO	P51, TMC7EP1, TMC7BIO	P45, TMC6EP1, TMC6BIO	P43, PIDBNZ, PIDPWMZ	P37, PIDBNI, PIDPWMX	N.C.	12
11	P65, DACOUT0	P67, DACOUT2	P64, TMC5BIO	P63, TMC5AIO	P57, TMC3AIO	P55, TMC2AIO	P52, TMC7EP2, TMC7CIO	P46, TMC6EP2, TMC6CIO	P42, PIDBPZ, PIDDIRZ	P40, PIDAPZ, PIDDIRY, TMC1AIO	N.C.	P36, PIDBPY, PIDDIRX	11
10	P70, DACOUT3	P71, DACOUT4	P66, DACOUT1	P61, TMC4AIO	VDD18	P54, CLKOUT	P50, TMC7EP0, TMC7AIO	P47, TMC6EP3, TMC6DIO	P41, PIDANZ, PIDPWMY, TMC1BIO	P34, PIDAPY, PIDFWDZ	P35, PIDANY, PIDREVZ	P33, PIDBNX, PIDREYV	10
9	VSS	P73, IRQ0	P72, DACOUT5	N.C.	N.C.	N.C.	VSS	P44, TMC6EP0, TMC6AIO	N.C.	P30, PIDAPX, PIDFWDX, SBI4	P32, PIDBPX, PIDFWDY, SBT4	P31, PIDANX, PIDREVX, SBO4	9
8	VSS	VDD5	VDD5	N.C.					N.C.	P27, IRQ5	VDD5	VSS	8
7	P75, ADIN01	P76, ADIN02	P74, ADIN00	N.C.					N.C.	VDD5	VSS	VDD5	7
6	P77, ADIN03	P81, ADIN05	P80, ADIN04	N.C.					N.C.	P24, SBO3	P26, IRQ4	P25, SBT3	6
5	P82, ADIN06	P84, ADIN08	P83, ADIN07	N.C.					N.C.	P21, SBO2	P23, SBI3	P22, SBT2	5
4	P85, IRQ1	Vref1+	Vref0+	N.C.	P97, IRQ2	VSS	N.C.	N.C.	N.C.	P16, SBO1	P20, SBI2	P17, SBT1	4
3	P86, ADIN10	P90, ADIN12	P87, ADIN11	P93, ADIN15	SDATA, TEST2	TEST3	P00, TM0IO	P03, TM3IO	P13, SBO0	P12, SBI0	P15, SBI1	P14, SBT0	3
2	P91, ADIN13	N.C.	P94, ADIN16	P95, ADIN17	SCLOCK, TEST1	OSCO	VPPEX	P02, TM2IO	P05, TM5IO	P06, TM6IO	P10, TMC0AIO	P11, TMC0BIO	2
1	N.C.	P92, ADIN14	P96, ADIN18	PA0, IRQ3	VDD18	OSCI	VDD5	NRST	P01, TM1IO	P04, TM4IO	P07, TM7IO	N.C.	1
	A	B	C	D	E	F	G	H	J	K	L	M	

## Request for your special attention and precautions in using the technical information and semiconductors described in this book

- (1) If any of the products or technical information described in this book is to be exported or provided to non-residents, the laws and regulations of the exporting country, especially, those with regard to security export control, must be observed.
- (2) The technical information described in this book is intended only to show the main characteristics and application circuit examples of the products. No license is granted in and to any intellectual property right or other right owned by Panasonic Corporation or any other company. Therefore, no responsibility is assumed by our company as to the infringement upon any such right owned by any other company which may arise as a result of the use of technical information described in this book.
- (3) The products described in this book are intended to be used for standard applications or general electronic equipment (such as office equipment, communications equipment, measuring instruments and household appliances).  
Consult our sales staff in advance for information on the following applications:
  - Special applications (such as for airplanes, aerospace, automobiles, traffic control equipment, combustion equipment, life support systems and safety devices) in which exceptional quality and reliability are required, or if the failure or malfunction of the products may directly jeopardize life or harm the human body.
  - Any applications other than the standard applications intended.
- (4) The products and product specifications described in this book are subject to change without notice for modification and/or improvement. At the final stage of your design, purchasing, or use of the products, therefore, ask for the most up-to-date Product Standards in advance to make sure that the latest specifications satisfy your requirements.
- (5) When designing your equipment, comply with the range of absolute maximum rating and the guaranteed operating conditions (operating power supply voltage and operating environment etc.). Especially, please be careful not to exceed the range of absolute maximum rating on the transient state, such as power-on, power-off and mode-switching. Otherwise, we will not be liable for any defect which may arise later in your equipment.
  - Even when the products are used within the guaranteed values, take into the consideration of incidence of break down and failure mode, possible to occur to semiconductor products. Measures on the systems such as redundant design, arresting the spread of fire or preventing glitch are recommended in order to prevent physical injury, fire, social damages, for example, by using the products.
- (6) Comply with the instructions for use in order to prevent breakdown and characteristics change due to external factors (ESD, EOS, thermal stress and mechanical stress) at the time of handling, mounting or at customer's process. When using products for which damp-proof packing is required, satisfy the conditions, such as shelf life and the elapsed time since first opening the packages.
- (7) This book may be not reprinted or reproduced whether wholly or partially, without the prior written permission of our company.