

# SOT223 NPN SILICON PLANAR MEDIUM POWER HIGH GAIN TRANSISTOR

ISSUE 3 - OCTOBER 1995

FZT692B


## FEATURES

- \* High Gain + Very low saturation voltage

## APPLICATIONS

- \* Darlington replacement
- \* Relay drivers, DC-DC converters

PARTMARKING DETAIL - FZT692B



## ABSOLUTE MAXIMUM RATINGS

PARAMETER	SYMBOL	VALUE	UNIT
Collector-Base Voltage	$V_{CBO}$	70	V
Collector-Emitter Voltage	$V_{CEO}$	70	V
Emitter-Base Voltage	$V_{EBO}$	5	V
Peak Pulse Current	$I_{CM}$	5	A
Continuous Collector Current	$I_C$	2	A
Power Dissipation at $T_{amb}=25^\circ\text{C}$	$P_{tot}$	2	W
Operating and Storage Temperature Range	$T_j:T_{stg}$	-55 to +150	°C

## ELECTRICAL CHARACTERISTICS (at $T_{amb} = 25^\circ\text{C}$ )

PARAMETER	SYMBOL	MIN.	TYP.	MAX.	UNIT	TEST CONDITIONS.
Breakdown Voltages	$V_{(BR)CBO}$	70			V	$I_C=100\mu\text{A}$
	$V_{(BR)CEO}$	70			V	$I_C=10\text{mA}^*$
	$V_{(BR)EBO}$	5			V	$I_E=100\mu\text{A}$
Cut-Off Currents	$I_{CBO}$			0.1	$\mu\text{A}$	$V_{CB}=55\text{V}$
	$I_{EBO}$			0.1	$\mu\text{A}$	$V_{EB}=4\text{V}$
Saturation Voltages	$V_{CE(\text{sat})}$			0.15	V	$I_C=0.1\text{A}, I_B=0.5\text{mA}^*$
				0.5	V	$I_C=1\text{A}, I_B=10\text{mA}^*$
				0.5	V	$I_C=2\text{A}, I_B=200\text{mA}^*$
	$V_{BE(\text{sat})}$			0.9	V	$I_C=1\text{A}, I_B=10\text{mA}^*$
Base-Emitter Turn-On Voltage	$V_{BE(on)}$			0.9	V	$I_C=1\text{A}, V_{CE}=2\text{V}^*$
Static Forward Current Transfer Ratio	$h_{FE}$	500 400 150				$I_C=100\text{mA}, V_{CE}=2\text{V}^*$ $I_C=500\text{mA}, V_{CE}=2\text{V}^*$ $I_C=1\text{A}, V_{CE}=2\text{V}^*$
Transition Frequency	$f_T$	150			MHz	$I_C=50\text{mA}, V_{CE}=5\text{V}, f=50\text{MHz}$
Input Capacitance	$C_{ibo}$		200		pF	$V_{EB}=0.5\text{V}, f=1\text{MHz}$
Output Capacitance	$C_{obo}$		12		pF	$V_{CB}=10\text{V}, f=1\text{MHz}$
Switching Times	$t_{on}$ $t_{off}$		46 1440		ns ns	$I_C=500\text{mA}, I_{B1}=50\text{mA}$ $I_{B2}=50\text{mA}, V_{CC}=10\text{V}$

\*Measured under pulsed conditions. Pulse width=300μs. Duty cycle ≤2%

Spice parameter data is available upon request for this device

# FZT692B

## TYPICAL CHARACTERISTICS

