

2SK3948G

Silicon N-channel junction FET

For impedance conversion in low frequency

For electret capacitor microphone

■ Features

- Low noise voltage NV
- High voltage gain GV
- Thin package: TSSSMini3-F2 (1.2 mm × 1.2 mm × 0.33 mm)

■ Package

- Code
TSSSMini3-F2
- Pin Name
1: Drain
2: Source
3: Gate

■ Absolute Maximum Ratings $T_a = 25^\circ\text{C}$

Parameter	Symbol	Rating	Unit
Drain-source voltage (Gate open)	V_{DSO}	20	V
Drain-gate voltage (Source open)	V_{DGO}	20	V
Drain-source current (Gate open)	I_{DSO}	2	mA
Drain-gate current (Source open)	I_{DGO}	2	mA
Power dissipation	P_{D}	100	mW
Operating ambient temperature	T_{opr}	-20 to +80	°C
Storage temperature	T_{stg}	-55 to +125	°C

■ Marking Symbol: 4X

■ Electrical Characteristics $T_a = 25^\circ\text{C} \pm 3^\circ\text{C}$

Parameter	Symbol	Conditions	Min	Typ	Max	Unit
Drain current *1	I_{D}	$V_{\text{DD}} = 2.0 \text{ V}, R_{\text{d}} = 2.2 \text{ k}\Omega \pm 1\%$	170		470	μA
Drain-source current *2	I_{DSS}	$V_{\text{DD}} = 2.0 \text{ V}, R_{\text{d}} = 2.2 \text{ k}\Omega \pm 1\%, V_{\text{GS}} = 0$	180		450	μA
Mutual conductance	g_{m}	$V_{\text{DS}} = 2.0 \text{ V}, V_{\text{GS}} = 0, f = 1 \text{ kHz}$	660	1500		μS
Noise voltage *3	NV	$V_{\text{DD}} = 2.0 \text{ V}, R_{\text{d}} = 2.2 \text{ k}\Omega \pm 1\%$ $C_{\text{O}} = 5 \text{ pF}, \text{A-curve}$			8	μV
Voltage gain	G_{V1}	$V_{\text{DD}} = 2.0 \text{ V}, R_{\text{d}} = 2.2 \text{ k}\Omega \pm 1\%$ $C_{\text{O}} = 5 \text{ pF}, e_{\text{G}} = 10 \text{ mV}, f = 1 \text{ kHz}$	-5.0	-1.0		dB
	G_{V2}	$V_{\text{DD}} = 12 \text{ V}, R_{\text{d}} = 2.2 \text{ k}\Omega \pm 1\%$ $C_{\text{O}} = 5 \text{ pF}, e_{\text{G}} = 10 \text{ mV}, f = 1 \text{ kHz}$	-3.0	3.0		
	G_{V3}	$V_{\text{DD}} = 1.5 \text{ V}, R_{\text{d}} = 2.2 \text{ k}\Omega \pm 1\%$ $C_{\text{O}} = 5 \text{ pF}, e_{\text{G}} = 10 \text{ mV}, f = 1 \text{ kHz}$	-7.0	-1.5		
Voltage gain difference	$\Delta G_{\text{V}} \cdot f $ *4	$V_{\text{DD}} = 2.0 \text{ V}, R_{\text{d}} = 2.2 \text{ k}\Omega \pm 1\%$ $C_{\text{O}} = 5 \text{ pF}, e_{\text{G}} = 10 \text{ mV}$ $f = 1 \text{ kHz to } 70 \text{ Hz}$		0.0	1.7	
	$ G_{\text{V1}} - G_{\text{V3}} $			0.5	1.0	dB

Note) 1. Measuring methods are based on JAPANESE INDUSTRIAL STANDARD JIS C 7030 measuring methods for transistors.

2. A protection diode is built-in between gate and source of transistor. However if forward current flows between gate and source transistor might be damaged. So please be careful not insert reverse.





3. *1: I_{D} is assured for I_{DSS} .

*2: Rank classification

Rank	T	U
$I_{\text{D}} (\mu\text{A})$	170 to 330	270 to 470
$I_{\text{DSS}} (\mu\text{A})$	180 to 320	280 to 450


*3: NV is assured for design.

*4: $\Delta |G_{\text{V}} \cdot f|$ is assured for AQL 0.065. (The measurement method is used by source-grounded circuit.)



TSSSMini3-F2

Unit: mm



Request for your special attention and precautions in using the technical information and semiconductors described in this book

- (1) If any of the products or technical information described in this book is to be exported or provided to non-residents, the laws and regulations of the exporting country, especially, those with regard to security export control, must be observed.
- (2) The technical information described in this book is intended only to show the main characteristics and application circuit examples of the products, and no license is granted under any intellectual property right or other right owned by our company or any other company. Therefore, no responsibility is assumed by our company as to the infringement upon any such right owned by any other company which may arise as a result of the use of technical information described in this book.
- (3) The products described in this book are intended to be used for standard applications or general electronic equipment (such as office equipment, communications equipment, measuring instruments and household appliances).
Consult our sales staff in advance for information on the following applications:
 - Special applications (such as for airplanes, aerospace, automobiles, traffic control equipment, combustion equipment, life support systems and safety devices) in which exceptional quality and reliability are required, or if the failure or malfunction of the products may directly jeopardize life or harm the human body.
 - Any applications other than the standard applications intended.
- (4) The products and product specifications described in this book are subject to change without notice for modification and/or improvement. At the final stage of your design, purchasing, or use of the products, therefore, ask for the most up-to-date Product Standards in advance to make sure that the latest specifications satisfy your requirements.
- (5) When designing your equipment, comply with the range of absolute maximum rating and the guaranteed operating conditions (operating power supply voltage and operating environment etc.). Especially, please be careful not to exceed the range of absolute maximum rating on the transient state, such as power-on, power-off and mode-switching. Otherwise, we will not be liable for any defect which may arise later in your equipment.
 - Even when the products are used within the guaranteed values, take into the consideration of incidence of break down and failure mode, possible to occur to semiconductor products. Measures on the systems such as redundant design, arresting the spread of fire or preventing glitch are recommended in order to prevent physical injury, fire, social damages, for example, by using the products.
- (6) Comply with the instructions for use in order to prevent breakdown and characteristics change due to external factors (ESD, EOS, thermal stress and mechanical stress) at the time of handling, mounting or at customer's process. When using products for which damp-proof packing is required, satisfy the conditions, such as shelf life and the elapsed time since first opening the packages.
- (7) This book may be not reprinted or reproduced whether wholly or partially, without the prior written permission of Matsushita Electric Industrial Co., Ltd.