


Tel: +44 118 979 1238 Fax: +44 118 979 1283

Email: info@actcrystals.com

The ACTR9001/980.0/QCC4A is a true one-port, surface-acoustic-wave (SAW) resonator in a surface-mount ceramic QCC4A case. It provides reliable, fundamental-mode, quartz frequency stabilization i.e. in transmitters or local oscillators operating at 980.000 MHz.

1.Package Dimension






2.

Pin	Configuration		
1	Input / Output		
3	Output / Input		
2/4	Case Ground		


Sign	Data (unit: mm)	Sign	Data (unit: mm)	
Α	1.2	D	1.4	
В	0.8	Е	5.0	
С	0.5	F	3.5	

3. Equivalent LC Model and Test Circuit




4. Typical Application Circuits

1) Low-Power Transmitter Application



2) Local Oscillator Application



Issue: 1.1 C1

Date: March 2010

 $In keeping \ with our ongoing \ policy \ of \ product \ evolvement \ and \ improvement, \ the \ above \ specification \ is \ subject \ to \ change \ without \ notice.$

ISO9001: 2000 Registered

For quotations or further information please contact us at: 3 The Business Centre, Molly Millars Lane, Wokingham, Berks, RG41 2EY, UK

http://www.actcrystals.com




+44 118 979 1238 Tel: Fax: +44 118 979 1283 Email: info@actcrystals.com


Issue: 1.1 C1

Date: March 2010

5. Typical Frequency Response



6.Temperature Characteristics



The curve shown above accounts for resonator contribution only and does not include oscillator temperature characteristics.

7.Performance

7-1.Maximum Ratings

Rating	Value	Units	
CW RF Power Dissipation	0	dBm	
DC Voltage Between Terminals	±30V	VDC	
Case Temperature	-40 to +85	°C	
Soldering Temperature	+250	°C	

7-2. Electronic Characteristics

	Characteristic	Sym	Minimum	Typical	Maximum	Units
Centre Frequency (+25 °C)	Absolute Frequency	f _C	979.850		980.150	MHz
	Tolerance from 980.000 MHz	Δf_{C}		±150		kHz
Insertion Loss		ΙL		1.5	2.2	dB
Quality Factor	Unloaded Q	Q _U		10,020		
	50 Ω Loaded Q	Q_L		1,600		
Temperature Stability	Turnover Temperature	T ₀	25		55	°C
	Turnover Frequency	f ₀		f _C		kHz
	Frequency Temperature Coefficient	FTC		0.032		ppm/°C 2
Frequency Aging Absolute Value during the First Year		fA		≤10		ppm/yr
DC Insulation Resistance Between Any Two Terminals			1.0			MΩ
RF Equivalent RLC Model	Motional Resistance	R_{M}		19	29	Ω
	Motional Inductance	L _M		30.9372		μΗ
	Motional Capacitance	См		0.8534		fF
	Shunt Static Capacitance	C ₀	2.05	2.35	2.65	pF

i CAUTION: Electrostatic Sensitive Device. Observe precautions for handling!

In keeping with our ongoing policy of product evolvement and improvement, the above specification is subject to change without notice.

ISO9001: 2000 Registered

For quotations or further information please contact us at: 3 The Business Centre, Molly Millars Lane, Wokingham, Berks, RG41 2EY, UK



Tel: +44 118 979 1238 Fax: +44 118 979 1283

Email: info@actcrystals.com

Issue: 1.1 C1

Date: March 2010

- 1. The centre frequency, f_C , is measured at the minimum IL point with the resonator in the 50 Ω test system.
- 2. Unless noted otherwise, case temperature $T_C = +25$ °C±2°C.
- Frequency aging is the change in f_C with time and is specified at +65°C or less. Aging may exceed the specification for prolonged temperatures above +65°C. Typically, aging is greatest the first year after manufacture, decreasing in subsequent years.
- 4. Turnover temperature, T_0 , is the temperature of maximum (or turnover) frequency, f_0 . The nominal frequency at any case temperature, T_0 , may be calculated from: $f = f_0 [1 FTC (T_0 T_0)^2]$.
- 5. This equivalent RLC model approximates resonator performance near the resonant frequency and is provided for reference only. The capacitance C₀ is the measured static (non-motional) capacitance between the two terminals. The measurement includes case parasitic capacitance.
- 6. Derived mathematically from one or more of the following directly measured parameters: f_C, IL, 3 dB bandwidth, f_C versus T_C, and C₀.
- 7. The specifications of this device are based on the test circuit shown above and subject to change or obsolescence without notice.
- 8. Typically, equipment utilizing this device requires emissions testing and government approval, which is the responsibility of the equipment manufacturer.
- 9. Our liability is only assumed for the Surface Acoustic Wave (SAW) component(s) per se, not for applications, processes and circuits implemented within components or assemblies.

In keeping with our ongoing policy of product evolvement and improvement, the above specification is subject to change without notice.