

No.3184

2SC4432

 ${\bf NPN\,Epitaxial\,Planar\,Silicon\,Transistor}\\ {\bf High-Frequency\,\,General-Purpose}$ 

## **Features**

- . High power gain
- · High cutoff frequency
- · Small cob, cre
- · Very small-sized package permitting the 2SC4432-applied sets to be made small and slim

$t Ta = 25^{\circ}C$		unit
$V_{CBO}$	40	V
$V_{CEO}$	18	v
	3	v
	50	mÅ
		mW
	_ <del></del>	°C
Tstg	-55  to  +150	°Č
	$egin{array}{c} V_{ ext{CEO}} \ V_{ ext{EBO}} \ I_{ ext{C}} \ P_{ ext{C}} \ T_{ ext{j}} \end{array}$	$\begin{array}{ccc} V_{CBO} & 40 \\ V_{CEO} & 18 \\ V_{EBO} & 3 \\ I_{C} & 50 \\ P_{C} & 250 \\ T_{J} & 150 \\ \end{array}$


Electrical Characteristics at Ta	$=25^{\circ}C$		min	typ	max	unit
Collector Cutoff Current	$I_{CBO}$	$V_{CB} = 18V, I_E = 0$			0.1	μA
Emitter Cutoff Current	$I_{EBO}$	$V_{EB} = 2V_{IC} = 0$			0.1	μA
DC Current Gain	$\mathbf{h_{FE}}$	$V_{CE} = 10V, I_C = 5mA$	60ж		270%	€ -
Gain-Bandwidth Product	$\mathbf{f_T}$	$V_{CE} = 10V, I_C = 5mA$		750		MHz
Output Capacitance	$\mathbf{c_{ob}}$	$V_{CB} = 10V, f = 1MHz$		0.7	1.2	рF
Reverse Transfer Capacitance	$c_{re}$	$V_{CB} = 10V, f = 1MHz$	(	0.45		рF
C-E Saturation Voltage	$V_{CE(sat)}$	$I_C = 10 \text{mA}, I_B = 1 \text{mA}$			0.2	v
B-C Time Constant	$r_{bb}$ ' $c_c$	$V_{CE} = 10V, I_{C} = 5mA, f = 31.9MHz$			23	ps
Power Gain	PG	$V_{CE} = 10V, I_{C} = 10mA, f = 100MHz$		28		ďΒ

%: The 2SC4432 is classified by 5mA hFE as follows.

			_		-				
60	3	120	90	4	180	135	5	270	7

Marking: RT h<sub>FE</sub> rank: 3,4,5

## PG Test Circuit




Unit (Capacitance : F)

 $L_1$ : 1mmø plated wire, 10mmø 5T, pitch 15mm, tap: 2T from base side

L<sub>2</sub>: 1mmø plated wire, 10mmø 7T, pitch 10mm,

tap : 2T from V<sub>C</sub> side

 ${f L_3}$  : 1mmø enamel wire, 10mmø 3T, pitch 10mm



- No products described or contained herein are intended for use in surgical implants, life-support systems, aerospace equipment, nuclear power control systems, vehicles, disaster/crime-prevention equipment and the like, the failure of which may directly or indirectly cause injury, death or property loss.
- Anyone purchasing any products described or contained herein for an above-mentioned use shall:
  - ① Accept full responsibility and indemnify and defend SANYO ELECTRIC CO., LTD., its affiliates, subsidiaries and distributors and all their officers and employees, jointly and severally, against any and all claims and litigation and all damages, cost and expenses associated with such use:
  - ② Not impose any responsibility for any fault or negligence which may be cited in any such claim or litigation on SANYO ELECTRIC CO., LTD., its affiliates, subsidiaries and distributors or any of their officers and employees jointly or severally.
- Information (including circuit diagrams and circuit parameters) herein is for example only; it is not guaranteed for volume production, SANYO believes information herein is accurate and reliable, but no guarantees are made or implied regarding its use or any infringements of intellectual property rights or other rights of third parties.