




Case Style	Type	Circuit	Type No.	I _o (A)	V _{FM} (V)	V _{RRM} (V)										
						20	30	40	50	60	90	100	200	300	400	600
 FLAT-PAK	Rectifier Diode	Single Chip	NSD03A10	3.0	1.0											
			NSD03A20													
			NSD03A40													
	Schottky Barrier Diode (S.B.D.)		NSQ03A02L	3.0	0.45											
			NSQ03A03		0.5											
			NSQ03A04		0.525											

Case Style	Type	Type No.	V _{V_{DD}} (V)	R _{ds} (Ω)	I _d (A)	Note
 TO-251/TO-252AA (Add suffix "F" for TO-252AA)	MOSFET (N-CHANNEL)	ME4N20	200	0.70	4.0	
		ME6N10	100	0.25	6.0	
		ME8N06E	60	0.15	8.0	
		ME12N06EL	60	0.18	12.0	Logic Level
		ME13N06E	60	0.12	13.0	
	MOSFET (P-CHANNEL)	ME4P06	-60	0.60	-4.0	
		ME8P06	-60	0.30	-8.0	

Case Style	0.9W SMD Zener Diodes					NZF Series			
	Part Number		V _Z (V)		I _Z (MA)	r _d (Ω)		I _s (MA)	
	Type	Suffix	Min	Max		Max	I _Z (MA)	Max	VR(V)
 D-64	NZF6.2	BP CP	5.8 6.2	6.6 7.0	40	6	40	20	3.0
	NZF6.8	BP CP	6.4 6.8	7.2 7.7	40	6	40	20	3.5
	NZF7.5	BP CP	7.0 7.5	7.9 8.4	40	4	40	20	4.0
	NZF8.2	BP CP	7.7 8.2	8.7 9.3	40	4	40	20	5.0
	NZF9.1	BP CP	8.5 9.1	9.6 10.2	40	6	40	20	6.0
	NZF10	BP CP	9.4 10.0	10.6 11.2	40	6	40	10	7.0
	NZF11	BP CP	10.4 11.0	11.6 12.3	20	8	20	10	8.0
	NZF12	BP CP	11.4 12.0	12.6 13.5	20	8	20	10	9.0
	NZF13	BP CP	12.4 13.3	14.1 15.0	20	10	20	10	10.0
	NZF15	BP CP	13.8 14.7	15.6 16.5	20	10	20	10	11.0
	NZF16	BP CP	15.3 16.2	17.1 18.3	20	12	20	10	12.0
	NZF18	BP CP	16.8 18.0	19.1 20.3	20	12	20	10	13.0
	NZF20	BP CP	18.8 20.0	21.2 22.4	20	14	20	10	15.0
	NZF22	BP CP	20.8 22.0	23.3 24.5	10	14	10	10	17.0
	NZF24	BP CP	22.8 24.0	25.6 27.6	10	16	10	10	19.0
	NZF27	BP CP	25.1 27.0	28.9 30.8	10	16	10	10	21.0
	NZF30	BP CP	28.0 30.0	32.0 34.0	10	18	10	10	23.0
	NZF33	BP CP	31.0 33.0	35.0 37.0	10	18	10	10	25.0
NZF36	BP CP	34.0 36.0	38.0 40.0	10	20	10	10	27.0	