

Silicijevе planarne signalne diode

Silicon planar signal diodes

Tip/Type		U_{BR}	I_{FAV}	U_F pri/at I_F		I_R		C	t_r		Sl./Fig.
		$100\mu A$	$\vartheta_{amb}=25^{\circ}C$	$\vartheta_{amb}=25^{\circ}C$		pri/at $25^{\circ}C$	pri/at U_R	pri/at 1 MHz $U_R=OV$			
		(V)	(mA)	(V)	(mA)	(nA)	(V)	(pF)	(ns)		
BA 511	1N4148	100	150	1.0	10	25	20	4	4^1	8^2	1
BA 513	1N4448	100	150	1.0	100	25	20	4	4^1	8^2	
BA 517	1N4150	70 $1\mu A$	200	1.0	200	100	50	2,5	4^2	4^2	
BA 518	1N4151	75 $5\mu A$	150	1.0	50	50	50	2	2^1	4^2	
BA 519	1N4152	40 $5\mu A$	150	0.88	20	50	30	2	2^1	4^2	
BA 520	1N4153	75 $5\mu A$	150	0.88	20	50	50	2	2^1	4^2	
BA 521	1N4154	35 $5\mu A$	150	1.0	30	100	25	4	2^1	4^2	
BA 523	1N4444	70 $5\mu A$	200	1.0	100	50	50	2	7^2	7^2	
BA 531	1N4727	30 $5\mu A$	150	0.85	10	100	20	4	4^2	4^2	
BA 533	1N4864	125	200	1.1	100	100	80	1.3	4^1	8^2	
BA 543	BAY 17	15	200	1.0	100	100	12	1.5	50^3	50^2	
BA 544	BAV 18	60	200	1.0	100	100	50	1.5	50^3	50^2	
BA 545	BAV 19	120	200	1.0	100	100	100	1.5	50^3	50^2	
BA 546	BAY 20	180	200	1.0	100	100	150	1.5	50^3	50^2	
BA 547	BAY 80	150	200	1.0	100	100	120	6	50^3	50^2	

* pri/at 100° C

¹ $I_F = 10 \text{ mA}$, $U_R = 6 \text{ V}$, $I_{RR} = 1 \text{ mA}$, $R_L = 100 \Omega$ ² $I_F = 10 \text{ mA}$, $I_R = 10 \text{ mA}$, $I_{RR} = 1 \text{ mA}$ ³ $I_F = 30 \text{ mA}$, $I_R = 30 \text{ mA}$, $I_{RR} = 3 \text{ mA}$, $R_L = 100 \Omega$

Silicijevе preklompne diode

Silicon switching diodes

Tip/Type	U_{RRM}	I_F	ϑ_{sig}	U_F pri/at I_F		C pri/at 1 MHz $U_R = 3 \text{ V}$	r_f pri/at $f = 100 \text{ MHz}$ $I_F = 10 \text{ mA}$	Sl./Fig.
	(V)	(mA)	(°C)	(V)	(mA)	(pF)	(Ω)	
BA 244 A	20	100	-50 do/to +100	<1	100	<1,8	0,5	1
BA 182 A	20	100	-40 do/to +100	<1,2	100	<1,25	0,7	2

Dioda s spremenljivo kapacitivnostjo

Capacitance diodes

Tip/Type	U_{RRM}	C_r pri/at U_R (1 MHz)		$\frac{C_r(U_{R1})}{C_r(U_{R2})}$	U_{R1}	U_{R2}	r_s	Sl./Fig.
	(V)	(pF)	(V)		(V)	(V)	(Ω)	
BB 105 A	30	2,3 do/to 2,8	25	4 do/to 5	3	25	0,8	2
BB 105 B		2 do/to 2,3	25	4,5 do/to 6	3	25	0,8	
BB 105 G		1,8 do/to 2,8	25	4 do/to 6	3	25	1,2	

