

June 1995

File Number

1412.2

## 8A, 100V - 200V Ultrafast Dual Diodes

The BYW51 series devices are low forward voltage drop, ultra-fast-recovery rectifiers (t<sub>RR</sub> < 35ns). They use a planar ion-implanted epitaxial construction.

These devices are intended for use as output rectifiers and fly-wheel diodes in a variety of high-frequency pulse-widthmodulated and switching regulators. Their low stored charge and attendant fast reverse-recovery behavior minimize electrical noise generation and in many circuits markedly reduce the turn-on dissipation of the associated power switching transistors.

## **Ordering Information**

#### **PACKAGING AVAILABILITY**

PART NUMBER	PACKAGE	BRAND		
BYW51-100	TO-220AB	BYW51100		
BYW51-150	TO-220AB	BYW51150		
BYW51-200	TO-220AB	BYW51200		

NOTE: When ordering, use the entire part number.

#### **Features**


- Ultra Fast Recovery Time (<35ns)
- Low Forward Voltage
- Low Thermal Resistance
- · Planar Design
- Wire-Bonded Construction

## **Applications**


- General Purpose
- · Power Switching Circuits to 100kHz
- Full-Wave Rectification

## Package

JEDEC TO-220AB



## Symbol



#### Absolute Maximum Ratings Per Junction

	BYW51-100	BYW51-150	BYW51-200	UNITS
Maximum Peak Repetitive Reverse Voltage V <sub>RRM</sub>	100	150	200	V
Maximum Peak Surge Voltage	110	165	220	V
Repetitive Peak Surge Current $I_{FRM}$ , $t_P < 10 \mu s$	100	100	100	Α
Nonrepetitive Peak Surge Current $I_F(RMS)$ , Total	20	20	20	Α
Average Rectified forward Current $I_{F(AV)}$ , Total $T_C = +125^{\circ}C$ , $a = 0.5$	8	8	8	Α
Repetitive Peak Surge Current. $I_{FSM}$ $t_P = 10$ ms, Sinusoidal	100	100	100	Α
Maximum Power Dissipation $P_D$ , $T_C = +125^{\circ}C$	20	20	20	W
Operating and Storage Temperature	-40 + 150	-40 + 150	-40 + 150	°C
$T_L$ (Lead Temperature During Soldering) At Distance > $^{1}/_{8}$ in. (3.17mm) From Case For 10s max.	260	260	260	°C

# BYW51-100, BYW51-150, BYW51-200

# Electrical Specifications Per Junction

	TEST CONDITIONS		LIMITS							
	°C	VOLTAGE V <sub>R</sub> V	CURRENT i <sub>F</sub> A	BYW51-100		BYW51-150		BYW51-200		
SYMBOL				MIN	MAX	MIN	MAX	MIN	MAX	UNITS
I <sub>R</sub>	25	100	-	-	5	-	-	-	-	μΑ
		150	-	-	-	-	5	-	-	μΑ
		200	-	-	-	-	-	-	5	μΑ
	100	100	-	-	1	-	-	-	-	mA
		150	-	-	-	-	1	-	-	mA
		200	-	-	-	-	-	-	1	mA
V <sub>F</sub>	25	-	8	-	0.95	-	0.95	-	0.95	٧
	100	-	8	-	0.89	-	0.89	-	0.89	V
t <sub>RR</sub>	25	-	1 (Note 1)	-	35	-	35	-	35	ns
R <sub>θJC</sub> , Per Leg		-	-	-	2.5	-	2.5	-	2.5	oC/M
R <sub>θJC</sub> , Total		-	-	-	1.3	-	1.3	-	1.3	oC/M
$R_{\theta JA}$		-	-	-	60	-	60	-	60	oC/W
CJ	25	10	0	All types (typ.) 40				pF		

### NOTE:

<sup>1.</sup>  $dI_F/dt > 50A/\mu s$ ,  $I_{RM}(rec) < 1A$ ,  $I_{RR} = 0.25A$ .

# **Typical Performance Curves**





FIGURE 1. PEAK SURGE FORWARD CURRENT vs SURGE DURATION

FIGURE 2. THERMAL IMPEDANCE vs PULSE WIDTH (PER JUNCTION)






FIGURE 3. TYPICAL FORWARD CURRENT vs FORWARD VOLTAGE DROP

FIGURE 4. TYPICAL REVERSE CURRENT vs VOLTAGE

All Intersil semiconductor products are manufactured, assembled and tested under ISO9000 quality systems certification.

Intersil semiconductor products are sold by description only. Intersil Corporation reserves the right to make changes in circuit design and/or specifications at any time without notice. Accordingly, the reader is cautioned to verify that data sheets are current before placing orders. Information furnished by Intersil is believed to be accurate and reliable. However, no responsibility is assumed by Intersil or its subsidiaries for its use; nor for any infringements of patents or other rights of third parties which may result from its use. No license is granted by implication or otherwise under any patent or patent rights of Intersil or its subsidiaries.

For information regarding Intersil Corporation and its products, see web site www.intersil.com

#### Sales Office Headquarters

**NORTH AMERICA** 

Intersil Corporation P. O. Box 883, Mail Stop 53-204 Melbourne, FL 32902

TEL: (321) 724-7000 FAX: (321) 724-7240 **EUROPE** 

Intersil SA Mercure Center 100, Rue de la Fusee 1130 Brussels, Belgium TEL: (32) 2.724.2111

FAX: (32) 2.724.22.05

ASIA

Intersil (Taiwan) Ltd. 7F-6, No. 101 Fu Hsing North Road Taipei, Taiwan Republic of China

TEL: (886) 2 2716 9310 FAX: (886) 2 2715 3029