

BAS16T, BAW56T, BAV70T, **BAV99T**




SURFACE MOUNT FAST SWITCHING DIODE

Features


- Ultra-Small Surface Mount Package
- Fast Switching Speed
- For General Purpose Switching Applications
- **High Conductance**
- Lead Free/RoHS Compliant (Note 1)


Mechanical Data


- Case: SOT-523, Molded Plastic
- Case material UL Flammability Rating 94V-0
- Moisture Sensitivity: Level 1 per J-STD-020C
- Terminals: Solderable per MIL-STD-202, Method 208
- Lead Free Plating (Matte Tin Finish).
- Polarity: See Diagrams Below
- Marking: See Diagrams Below & Page 3
- Ordering Information, see Page 2
- Weight: 0.002 grams (approximate)




	SOT-523									
Dim	Min	Max	Тур							
Α	0.15	0.30	0.22							
В	0.75	0.85	0.80							
С	1.45	1.75	1.60							
D	_	_	0.50							
G	0.90	1.10	1.00							
Н	1.50	1.70	1.60							
J	0.00	0.10	0.05							
K	0.60	0.80	0.75							
L	0.10	0.30	0.22							
M	0.10	0.20	0.12							
N	0.45	0.65	0.50							
α	0°	8°	_							
All D	All Dimensions in mm									









Maximum Ratings @ T_A = 25°C unless otherwise specified

Characteristic	Symbol	Value	Unit
Peak Repetitive Reverse Voltage Working Peak Reverse Voltage DC Blocking Voltage	V _{RRM} V _{RWM} V _R	85	V
RMS Reverse Voltage	V _{R(RMS)}	60	V
Forward Continuous Current (Note 2) Single diode Double diode	I _{FM}	155 75	mA
Repetitive Peak Forward Current	I _{FRM}	500	mA
Non-Repetitive Peak Forward Surge Current @ t = 1.0 \(\mu \) s @ t = 1.0 \(\mu \) s @ t = 1.0 s	I _{FSM}	4.0 1.0 0.5	А
Power Dissipation (Note 2)	Pd	150	mW
Thermal Resistance Junction to Ambient (Note 2)	R ₀ JA	833	°C/W
Operating and Storage Temperature Range	T _j , T _{STG}	-65 to +150	°C


- 1. No purposefully added lead.
- 2. Device mounted on FR-4 PC board with recommended pad layout, which can be found on our website at http://www.diodes.com/datasheets/ap02001.pdf.




Electrical Characteristics @ T_A = 25°C unless otherwise specified

Characteristic	Symbol	Min	Тур	Max	Unit	Test Condition
Reverse Breakdown Voltage (Note 3)	V _{(BR)R}	85	_	_	V	$I_R = 100 \mu A$
Forward Voltage	V _F	_	_	0.715 0.855 1.0 1.25	V	I _F = 1.0mA I _F = 10mA I _F = 50mA I _F = 150mA
Leakage Current (Note 3)	I _R	_	_	2.0 100 60 30	μΑ μΑ μΑ nA	$V_R = 75V$ $V_R = 75V$, $T_j = 150$ °C $V_R = 25V$, $T_j = 150$ °C $V_R = 25V$
Total Capacitance	Ст		1.5	_	pF	V _R = 0, f = 1.0MHz
Reverse Recovery Time	t _{rr}	_	_	4.0	ns	$I_F = I_R = 10 \text{mA},$ $I_{rr} = 0.1 \text{ x } I_R, R_L = 100 \Omega$


Notes: 3. Short duration test pulse to minimize self-heating effect.




T_S, SOLDERING POINT TEMPERATURE (°C) Fig. 1 Current Derating Curve



V_R, INSTANTANEOUS REVERSE VOLTAGE (V) Fig. 3 Typical Reverse Characteristics



 V_{F} , INSTANTANEOUS FORWARD VOLTAGE (V) Fig. 2 Forward Characteristics



 $\label{eq:VR} {\rm V_R,\,REVERSE\,\,VOLTAGE\,\,(V)}$ Fig. 4 Typical Capacitance vs. Reverse Voltage


Ordering Information (Note 4)

Device	Packaging	Shipping
BAS16T-7-F	SOT-523	3000/Tape & Reel
BAW56T-7-F	SOT-523	3000/Tape & Reel
BAV70T-7-F	SOT-523	3000/Tape & Reel
BAV99T-7-F	SOT-523	3000/Tape & Reel

Notes: 4. For Packaging Details, go to our website at http://www.diodes.com/datasheets/ap02007.pdf.



Marking Information



XX = Product Type Marking Code (See Page 1, e.g. A2 = BAS16T)

YM = Date Code Marking Y = Year (ex: N = 2002) M = Month (ex: 9 = September)

Date Code Key

Year	2002	2003	2004	2005	2006	2007	2008	2009	2010	2011	2012
Code	N	Р	R	S	Т	U	V	W	Χ	Υ	Z

Month	Jan	Feb	March	Apr	May	Jun	Jul	Aug	Sep	Oct	Nov	Dec
Code	1	2	3	4	5	6	7	8	9	0	Ν	D

IMPORTANT NOTICE

Diodes Incorporated and its subsidiaries reserve the right to make modifications, enhancements, improvements, corrections or other changes without further notice to any product herein. Diodes Incorporated does not assume any liability arising out of the application or use of any product described herein; neither does it convey any license under its patent rights, nor the rights of others. The user of products in such applications shall assume all risks of such use and will agree to hold Diodes Incorporated and all the companies whose products are represented on our website, harmless against all damages.

LIFE SUPPORT

Diodes Incorporated products are not authorized for use as critical components in life support devices or systems without the expressed written approval of the President of Diodes Incorporated.