Unit: mm

TOSHIBA Field Effect Transistor Silicon N-Channel MOS Type (π -MOS V)

# 2SK4021

### Switching Regulator and DC/DC Converter Applications Motor Drive Applications

• Low drain-source ON-resistance :  $R_{DS}$  (ON) = 0.8  $\Omega$  (typ.) • High forward transfer admittance :  $|Y_{fs}|$  = 4.5 S (typ.) • Low leakage current :  $I_{DSS}$  = 100  $\mu$ A (max) ( $V_{DS}$  = 250 V) • Enhancement mode :  $V_{th}$  = 1.5~3.5 V ( $V_{DS}$  = 10 V,  $I_{D}$  = 1 mA)

#### **Absolute Maximum Ratings (Ta = 25°C)**

Character	stic	Symbol	Rating	Unit
Drain-source voltage		$V_{DSS}$	250	V
Drain-gate voltage (Ro	<sub>SS</sub> = 20 kΩ)	$V_{DGR}$	250	V
Gate-source voltage		V <sub>GSS</sub>	±20	V
Drain current	DC (Note 1)	I <sub>D</sub>	4.5	Α
	Pulse (Note 1)	I <sub>DP</sub>	18	Α
Drain power dissipation	n (Tc = 25°C)	P <sub>D</sub>	20	W
Single-pulse avalanche	e energy (Note 2)	E <sub>AS</sub>	51	mJ
Avalanche current		I <sub>AR</sub>	4.5	Α
Repetitive avalanche e	nergy (Note 3)	E <sub>AR</sub>	2.0	mJ
Channel temperature		T <sub>ch</sub>	150	°C
Storage temperature ra	ange	T <sub>stg</sub>	-55~150	°C

0.6 MAX 0.6 MAX 0.6 MAX 0.6 MAX 0.6 MAX

2-7J2B

Weight: 0.36 g (typ.)

JEDEC JEITA TOSHIBA

1. GATE
2. DRAIN
(HEAT SINK)
3. SOURCE

Note: Using continuously under heavy loads (e.g. the application of high temperature/current/voltage and the significant change in temperature, etc.) may cause this product to decrease in the reliability significantly even if the operating conditions (i.e. operating temperature/current/voltage, etc.) are within the absolute maximum ratings. Please design the appropriate reliability upon reviewing the Toshiba Semiconductor Reliability Handbook ("Handling Precautions"/Derating Concept and Methods) and individual reliability data (i.e. reliability test report and estimated failure rate, etc).

#### Thermal Characteristics

Characteristic	Symbol	Max	Unit
Thermal resistance, channel to case	R <sub>th (ch-c)</sub>	6.25	°C / W
Thermal resistance, channel to ambient	R <sub>th (ch-a)</sub>	125	°C/W

Note 1: Ensure that the channel temperature does not exceed 150°C.

Note 2:  $V_{DD}$  = 50 V,  $T_{ch}$  = 25°C (initial), L = 4.28 mH,  $R_G$  = 25  $\Omega$ ,  $I_{AR}$  = 4.5 A

Note 3: Repetitive rating: pulse width limited by maximum channel temperature

This transistor is an electrostatic-sensitive device. Handle with care.

## **Electrical Characteristics (Ta = 25°C)**


**TOSHIBA** 

Chara	cteristic	Symbol	Test Condition	Min	Тур.	Max	Unit
Gate leakage cu	urrent	I <sub>GSS</sub>	V <sub>GS</sub> = ±16 V, V <sub>DS</sub> = 0 V	_	_	±10	μΑ
Drain cutoff curr	rent	I <sub>DSS</sub>	V <sub>DS</sub> = 250 V, V <sub>GS</sub> = 0 V	_	_	100	μΑ
Drain-source b	reakdown voltage	V (BR) DSS	I <sub>D</sub> = 10 mA, V <sub>GS</sub> = 0 V	250	_		V
Gate threshold	voltage	V <sub>th</sub>	V <sub>DS</sub> = 10 V, I <sub>D</sub> = 1 mA	1.5	_	3.5	V
Drain-source O	N-resistance	R <sub>DS</sub> (ON)	V <sub>GS</sub> = 10 V, I <sub>D</sub> = 2.5 A	_	0.8	1.0	Ω
Forward transfe	r admittance	Y <sub>fs</sub>	V <sub>DS</sub> = 10 V, I <sub>D</sub> = 2.5 A	2.0	4.5		S
Input capacitano	ce	C <sub>iss</sub>		_	440		
Reverse transfe	r capacitance	C <sub>rss</sub>	V <sub>DS</sub> = 10 V, V <sub>GS</sub> = 0 V, f = 1 MHz	_	35		pF
Output capacita	nce	C <sub>oss</sub>		_	120	_	
	Rise time	tr	V <sub>GS</sub> 10V I I I OUT	_	15	_	
Switching time	Turn-on time	t <sub>on</sub>	$R_L$	_	20	_	20
Switching time Fall time	Fall time	t <sub>f</sub>	v <sub>DD</sub> =100V	_	15		- ns
	Turn-off time	t <sub>off</sub>	$\begin{array}{c} V_{DD} = 100 V \\ Duty \leq 1\%, \ t_{W} = 10 \mu s \end{array}$	_	60	-	
Total gate charge (gate-source plus gate-drain)			_	10	_		
Gate-source charge		Q <sub>gs</sub>	$V_{DD} = 100 \text{ V}, V_{GS} = 10 \text{ V}, I_D = 4.5 \text{ A}$		6	_	nC
Gate-drain ("Miller") charge		Q <sub>gd</sub>		_	4	_	


# Source-Drain Ratings and Characteristics (Ta = 25°C)


Characteristic	Symbol	Test Condition	Min	Тур.	Max	Unit
Continuous drain reverse current (Note 1)	I <sub>DR</sub>	_	_	_	4.5	Α
Pulse drain reverse current (Note 1)	I <sub>DRP</sub>	_	_	_	18	Α
Forward voltage (diode)	V <sub>DSF</sub>	I <sub>DR</sub> = 4.5 A, V <sub>GS</sub> = 0 V	_	_	-2.0	V
Reverse recovery time	t <sub>rr</sub>	I <sub>DR</sub> = 4.5 A, V <sub>GS</sub> = 0 V		110	_	ns
Reverse recovery charge	Q <sub>rr</sub>	dI <sub>DR</sub> / dt = 100 Å / μs	_	0.47	_	μС


#### Marking





2 2007-07-24



















3


















4









$$R_G = 25 \Omega$$
  
 $V_{DD} = 50 \text{ V}, L = 4.28\text{mH}$ 

$$\mathsf{EAS} = \frac{1}{2} \cdot L \cdot l^2 \cdot \left( \frac{\mathsf{BVDSS}}{\mathsf{BVDSS} - \mathsf{VDD}} \right)$$

5 2007-07-24

#### **RESTRICTIONS ON PRODUCT USE**

20070701-EN

- The information contained herein is subject to change without notice.
- TOSHIBA is continually working to improve the quality and reliability of its products. Nevertheless, semiconductor devices in general can malfunction or fail due to their inherent electrical sensitivity and vulnerability to physical stress. It is the responsibility of the buyer, when utilizing TOSHIBA products, to comply with the standards of safety in making a safe design for the entire system, and to avoid situations in which a malfunction or failure of such TOSHIBA products could cause loss of human life, bodily injury or damage to property.
  In developing your designs, please ensure that TOSHIBA products are used within specified operating ranges as set forth in the most recent TOSHIBA products specifications. Also, please keep in mind the precautions and conditions set forth in the "Handling Guide for Semiconductor Devices," or "TOSHIBA Semiconductor Reliability Handbook" etc.
- The TOSHIBA products listed in this document are intended for usage in general electronics applications (computer, personal equipment, office equipment, measuring equipment, industrial robotics, domestic appliances, etc.). These TOSHIBA products are neither intended nor warranted for usage in equipment that requires extraordinarily high quality and/or reliability or a malfunction or failure of which may cause loss of human life or bodily injury ("Unintended Usage"). Unintended Usage include atomic energy control instruments, airplane or spaceship instruments, transportation instruments, traffic signal instruments, combustion control instruments, medical instruments, all types of safety devices, etc.. Unintended Usage of TOSHIBA products listed in his document shall be made at the customer's own risk.
- The products described in this document shall not be used or embedded to any downstream products of which manufacture, use and/or sale are prohibited under any applicable laws and regulations.
- The information contained herein is presented only as a guide for the applications of our products. No responsibility is assumed by TOSHIBA for any infringements of patents or other rights of the third parties which may result from its use. No license is granted by implication or otherwise under any patents or other rights of TOSHIBA or the third parties.
- Please contact your sales representative for product-by-product details in this document regarding RoHS
  compatibility. Please use these products in this document in compliance with all applicable laws and regulations
  that regulate the inclusion or use of controlled substances. Toshiba assumes no liability for damage or losses
  occurring as a result of noncompliance with applicable laws and regulations.

6