

### **Features**

- ► Low threshold -2.4V max.
- High input impedance
- ► Low input capacitance 125pF max.
- Fast switching speeds
- Low on resistance
- Free from secondary breakdown
- Low input and output leakage
- Complementary N and P-channel devices

### **Applications**


- ▶ Logic level interfaces ideal for TTL and CMOS
- Solid state relays
- Battery operated systems
- Photo voltaic drives
- Analog switches
- General purpose line drivers
- Telecom switches


### **General Description**

These low threshold enhancement-mode (normally-off) transistors utilize a vertical DMOS structure and Supertex's well-proven silicon-gate manufacturing process. This combination produces devices with the power handling capabilities of bipolar transistors and with the high input impedance and positive temperature coefficient inherent in MOS devices. Characteristic of all MOS structures, these devices are free from thermal runaway and thermally-induced secondary breakdown.

Supertex's vertical DMOS FETs are ideally suited to a widerange of switching and amplifying applications where very low threshold voltage, high breakdown voltage, high input impedance, low input capacitance, and fast switching speeds are desired.

### **Switching Waveforms and Test Circuit**





### **Thermal Characteristics**

Package	I <sub>D</sub> continuous <i>†</i> (mA)	I <sub>D</sub> pulsed (A)	Power Dissipation @ T <sub>A</sub> = 25°C (W)	<b>θ</b> <sub>jc</sub> (°C/W)	<b>θ</b> <sub>jc</sub> (°C/W)	l <sub>DR</sub> † (mA)	I <sub>DRM</sub> (A)
TO-243AA	-480	-2.5	1.6‡	15	78‡	-480	-2.5

 $f_{D}$  (continuous) is limited by max rated  $T_{D}$ 

<sup>#</sup> Mounted on FR5 board, 25mm x 25mm x 1.57mm.

**Ordering Information** 

Device	Package Opt	ions	BV <sub>DSS</sub> /BV <sub>DGS</sub>	R <sub>DS(ON)</sub>	V <sub>GS(TH)</sub>	I <sub>D(ON)</sub>	
Device	TO-243AA (SOT-89)	TO-243AA (SOT-89)		(Ω)	(max) (V)	(min) (A)	
TP2510	TP2510N8-G	TP2510ND	-100	3.5	-2.4	-1.5	

<sup>\*</sup> MIL visual screening available.

<sup>-</sup>G indicates package is RoHS compliant ('Green')






### **Absolute Maximum Ratings**

Parameter	Value
Drain-to-source voltage	$BV_{\mathtt{DSS}}$
Drain-to-gate voltage	$BV_{\mathtt{DGS}}$
Gate-to-source voltage	±20V
Operating and storage temperature	-55°C to +150°C
Soldering temperature*	300°C

<sup>\*</sup> Distance of 1.6 mm from case for 10 seconds.

Absolute Maximum Ratings are those values beyond which damage to the device may occur. Functional operation under these conditions is not implied. Continuous operation of the device at the absolute rating level may affect device reliability. All voltages are referenced to device ground.

# **Pin Configuration**



## **Product Marking**



W = Code for Week Sealed
\_\_\_\_ = "Green" Packaging

TO-243AA (SOT-89) N8


# Electrical Characteristics (@25°C unless otherwise specified)

Symbol	Parameter	Min	Тур	Max	Units	Conditions		
BV <sub>DSS</sub>	Drain-to-source breakdown voltage  Gate threshold voltage		-	-	V	V <sub>GS</sub> = 0V, ID = -2.0mA		
V <sub>GS(th)</sub>			-	-2.4	V	$V_{GS} = V_{DS}$ , ID= -1.0mA		
$\Delta V_{GS(th)}$	Change in V <sub>GS(th)</sub> with temperature	-	-	5.0	mV/°C	$V_{GS} = V_{DS}$ , ID= -1.0mA		
I <sub>GSS</sub>	Gate body leakage	-	-	-100	nA	$V_{GS} = \pm 20V, V_{DS} = 0V$		
		-	-	-10	μA	$V_{GS} = 0V, V_{DS} = Max Rating$		
I <sub>DSS</sub>	Zero gate voltage drain current		-	-1.0	mA	$V_{GS} = 0V$ , $V_{DS} = 0.8$ Max Rating, $T_A = 125^{\circ}C$		
	ON state due in summer	-0.4	-0.6	-	_	V <sub>GS</sub> = -5.0V, V <sub>DS</sub> = -25V		
I <sub>D(ON)</sub>	ON-state drain current	-1.5	-2.5	-	A	V <sub>GS</sub> = -10V, V <sub>DS</sub> = -25V		
В	Static drain-to-source ON-State	-	5.0	7.0	Ω	V <sub>GS</sub> = -5.0V, ID = -250mA		
R <sub>DS(ON)</sub>	Resistance		2.0	3.5	1 12	V <sub>GS</sub> = -10V, ID = -0.75A		
$\Delta R_{DS(ON)}$	Change in R <sub>DS(ON)</sub> with temperature	-	-	1.7	%/°C	V <sub>GS</sub> = -10V, ID = -0.75A		
G <sub>FS</sub>	Forward transconductance		360	-	mmho	V <sub>DS</sub> = -25V, ID = -0.75A		
C <sub>ISS</sub>	Input capacitance	-	80	125		V <sub>GS</sub> = 0V,		
C <sub>oss</sub>	Common source output capacitance		40	70	pF	$V_{DS} = -25V$ ,		
C <sub>RSS</sub>	Reverse transfer capacitance	-	10	25		f = 1.0 MHz		
t <sub>d(ON)</sub>	Turn-ON delay time	-	-	10		V <sub>DD</sub> = -25V,		
t <sub>r</sub>	Rise time	-	-	15	ne			
t <sub>d(OFF)</sub>	Turn-OFF delay time		-	20	ns	$\begin{vmatrix} I_D = -1.0A, \\ R_{GEN} = 25\Omega \end{vmatrix}$		
t <sub>f</sub>	Fall time	-	-	15		GEIN		
V <sub>SD</sub>	Diode forward voltage drop	-	-	-1.8	V	$V_{GS} = 0V, I_{SD} = -1.0A$		
t <sub>rr</sub>	Reverse recovery time	-	300	-	ns	$V_{GS} = 0V, I_{SD} = -1.0A$		


#### Notes:

- 1. All D.C. parameters 100% tested at 25°C unless otherwise stated. (Pulse test: 300µs pulse, 2% duty cycle.)
- 2. All A.C. parameters sample tested.


### **Typical Performance Curves**




#### Transconductance vs. Drain Current




Maximum Rated Safe Operating Area




#### **Saturation Characteristics**



#### Power Dissipation vs. Ambient Temperature



### Thermal Response Characteristics



 $V_{GS} = -10V$ 

-3.2

-4.0

2.0

1.6

1.2


0


150


100

R<sub>DS(ON)</sub> (normalized)


# **Typical Performance Curves**







# 3-Lead TO-243AA (SOT-89) Package Outline (N8)



Symbo	ol	Α	b	b1	С	D	D1	Е	E1	е	e1	н	L
	MIN	1.40	0.44	0.36	0.35	4.40	1.62	2.29	2.13	1.50 3.00 BSC BSC	3.94	0.89	
Dimensions (mm)	NOM	-	-	-	-	1	-	-	-		-	-	
()	MAX	1.60	0.56	0.48	0.44	4.60	1.83	2.60	2.29		ВЗС	4.25	1.20

JEDEC Registration TO-243, Variation AA, Issue C, July 1986. **Drawings not to scale**.

(The package drawing(s) in this data sheet may not reflect the most current specifications. For the latest package outline information go to <a href="http://www.supertex.com/packaging.html">http://www.supertex.com/packaging.html</a>.)

**Supertex inc.** does not recommend the use of its products in life support applications, and will not knowingly sell its products for use in such applications, unless it receives an adequate "product liability indemnification insurance agreement". **Supertex** does not assume responsibility for use of devices described and limits its liability to the replacement of the devices determined defective due to workmanship. No responsibility is assumed for possible omissions or inaccuracies. Circuitry and specifications are subject to change without notice. For the latest product specifications, refer to the **Supertex** website: http://www.supertex.com.

©2007 **Supertex inc.** All rights reserved. Unauthorized use or reproduction is prohibited.

