


Tel: +44 118 979 1238 Fax: +44 118 979 1283

Email: info@actcrystals.com

The ACTR980/980.0/TO39 is a true one-port, surface-acoustic-wave (SAW) resonator in a low-profile metal TO-39 case. It provides reliable, fundamental-mode, quartz frequency stabilization i.e. in transmitters or local oscillators operating at 980.000 MHz.

1.Package Dimension (TO-39)




2.

Pin	Configuration			
1	Input / Output			
2	Output / Input			
3	Case Ground			


Dimension	Data (unit: mm)				
А	9.30±0.20				
В	5.08±0.10				
С	3.40±0.20				
D	3±0.20/5±0.20				
Е	0.45±0.20				

3. Equivalent LC Model and Test Circuit




4. Typical Application Circuits

1) Low-Power Transmitter Application



2) Local Oscillator Application



Issue: 1 C1

Date: SEPT 04

In keeping with our ongoing policy of product evolvement and improvement, the above specification is subject to change without notice.

ISO9001: 2000 Registered - Registration number 6830/2

For quotations or further information please contact us at:

3 The Business Centre, Molly Millars Lane, Wokingham, Berks, RG41 2EY, UK

http://www.actcrystals.com




Tel: +44 118 979 1238 Fax: +44 118 979 1283

Issue: 1 C1


Date: SEPT 04

Email: info@actcrystals.com

5. Typical Frequency Response



6.Temperature Characteristics



The curve shown above accounts for resonator contribution only and does not include oscillator temperature characteristics.

7.Performance

7-1.Maximum Ratings

Rating	Value	Units
CW RF Power Dissipation	0	dBm
DC Voltage Between Any Two Pins	±30V	VDC
Case Temperature	-40 to +85	°C

7-2. Electronic Characteristics

7 Z.Electronic Orientacionstics									
	Characteristic	Sym	Minimum	Typical	Maximum	Units			
Centre Frequency (+25 °C)	Absolute Frequency	f _C	979.850		980.150	MHz			
	Tolerance from 980.000MHz	Δf_{C}		±150		kHz			
Insertion Loss		IL		1.3	1.8	dB			
Quality Factor	Unloaded Q	Q _U		10,880					
	50 Ω Loaded Q	Q_L		1,500					
Temperature Stability	Turnover Temperature	T ₀	25		55	°C			
	Turnover Frequency	f ₀		f _C		kHz			
	Frequency Temperature Coefficient	FTC		0.032		ppm/°C 2			
Frequency Aging Absolute Value during the First Year		f _A		≤10		ppm/yr			
DC Insulation Resistance Between Any Two Pins			1.0			МΩ			
RF Equivalent RLC Model	Motional Resistance	R _M		16	23	Ω			
	Motional Inductance	L _M		28.2725		μН			
	Motional Capacitance	См		0.9338		fF			
	Pin 1 to Pin 2 Static Capacitance	C ₀	2.05	2.35	2.65	pF			

In keeping with our ongoing policy of product evolvement and improvement, the above specification is subject to change without notice.

ISO9001: 2000 Registered - Registration number 6830/2

For quotations or further information please contact us at:

3 The Business Centre, Molly Millars Lane, Wokingham, Berks, RG41 2EY, UK



Tel: +44 118 979 1238 Fax: +44 118 979 1283

Email: info@actcrystals.com

i CAUTION: Electrostatic Sensitive Device. Observe precautions for handling!

- 1. The centre frequency, f_C , is measured at the minimum IL point with the resonator in the 50 Ω test system.
- 2. Unless noted otherwise, case temperature $T_C = +25^{\circ}C \pm 2^{\circ}C$.
- Frequency aging is the change in f_C with time and is specified at +65°C or less. Aging may exceed the specification for prolonged temperatures above +65°C. Typically, aging is greatest the first year after manufacture, decreasing in subsequent years.
- 4. Turnover temperature, T_0 , is the temperature of maximum (or turnover) frequency, f_0 . The nominal frequency at any case temperature, T_0 , may be calculated from: $f = f_0 [1 FTC (T_0 T_0)^2]$.
- 5. This equivalent RLC model approximates resonator performance near the resonant frequency and is provided for reference only. The capacitance C₀ is the measured static (non-motional) capacitance between Pin1 and Pin2. The measurement includes case parasitic capacitance.
- 6. Derived mathematically from one or more of the following directly measured parameters: f c, IL, 3 dB bandwidth, fc versus Tc, and Co.
- The specifications of this device are based on the test circuit shown above and subject to change or obsolescence without notice.
- 8. Typically, equipment utilizing this device requires emissions testing and government approval, which is the responsibility of the equipment manufacturer.
- 9. Our liability is only assumed for the Surface Acoustic Wave (SAW) component(s) per se, not for applications, processes and circuits implemented within components or assemblies.

In keeping with our ongoing policy of product evolvement and improvement, the above specification is subject to change without notice.

ISO9001: 2000 Registered - Registration number 6830/2

Issue: 1 C1