



Tel: +44 118 979 1238 Fax: +44 118 979 1283

Email: info@actcrystals.com

The ACTR303/303.825/F-11 is a true one-port, surface-acoustic-wave (SAW) resonator in a low-profile metal F-11 case. It provides reliable, fundamental-mode, quartz frequency stabilization i.e. in transmitters or local oscillators operating at 303.825 MHz.

1.Package Dimension (F-11)






Pin	Configuration
1,4	Input / Output
2/3	Case Ground


Dimension	Data (unit: mm)		
А	11.0±0.3		
В	4.5±0.3		
С	3.2±0.3		
D	0.45±0.1		
Е	5.0±0.5		
F	2.54±0.2		

3. Equivalent LC Model and Test Circuit




4.Typical Application Circuits

1) Low-Power Transmitter Application



2) Local Oscillator Application



Issue: 1 C1

Date: SEPT 04

In keeping with our ongoing policy of product evolvement and improvement, the above specification is subject to change without notice.

ISO9001: 2000 Registered - Registration number 6830/2

For quotations or further information please contact us at:

3 The Business Center, Molly Millars Lane, Wokingham, Berks, RG41 2EY, UK

http://www.actcrystals.com




Tel : +44 118 979 1238
Fax : +44 118 979 1283

Issue: 1 C1


Date: SEPT 04

Email: info@actcrystals.com

5. Typical Frequency Response



6.Temperature Characteristics



The curve shown above accounts for resonator contribution only and does not include oscillator temperature characteristics.

7.Performance

7-1.Maximum Ratings

Rating	Value	Units
CW RF Power Dissipation	0	dBm
DC Voltage Between Terminals	±30V	VDC
Case Temperature	-40 to +85	°C

7-2. Electronic Characteristics

	Characteristic	Sym	Minimum	Typical	Maximum	Units
Centre Frequency	Absolute Frequency	fc	303.750		303.900	MHz
(+25°C)	Tolerance from 303.825MHz	Δf_{C}		±75		kHz
Insertion Loss		IL		1.3	1.8	dB
Ouglity Factor	Unloaded Q	Q _U		15,250		
Quality Factor	50 Ω Loaded Q	Q _L		2,100		
	Turnover Temperature	T ₀	25		55	°C
Temperature Stability	Turnover Frequency	fo		fc		kHz
	Frequency Temperature Coefficient	FTC		0.032		ppm/°C 2
Frequency Aging Absolute Value during the First Year		f _A		≤10		ppm/yr
DC Insulation Resis	tance Between Any Two Pins		1.0			MΩ
	Motional Resistance	R _M		16	23	Ω
RF Equivalent	Motional Inductance	L _M		127.6716		μН
RLC Model	Motional Capacitance	См		2.1515		fF
	Pin 1 to Pin 4 Static Capacitance	C ₀	2.1	2.4	2.7	pF

1 CAUTION: Electrostatic Sensitive Device. Observe precautions for handling!

In keeping with our ongoing policy of product evolvement and improvement, the above specification is subject to change without notice.

ISO9001: 2000 Registered - Registration number 6830/2

For quotations or further information please contact us at:

3 The Business Center, Molly Millars Lane, Wokingham, Berks, RG41 2EY, UK



Tel: +44 118 979 1238 +44 118 979 1283 Fax: Email: info@actcrystals.com

- 1. The centre frequency, f_C , is measured at the minimum IL point with the resonator in the 50 Ω test system.
- Unless noted otherwise, case temperature $T_C = +25^{\circ}C \pm 2^{\circ}C$.
- Unless noted otherwise, case temperature IC = +25°C±2 G.
 Frequency aging is the change in f_C with time and is specified at +65°C or less. Aging may exceed the specification for prolonged temperatures above +65°C. Typically, aging is greatest the first year after manufacture, decreasing in subsequent years.
- 4. Turnover temperature, To, is the temperature of maximum (or turnover) frequency, fo. The nominal frequency at any case temperature, T_C , may be calculated from: $f = f_0 [1 - FTC (T_0 - T_C)^2]$.
- This equivalent RLC model approximates resonator performance near the resonant frequency and is provided for reference only. The capacitance C₀ is the measured static (nonmotional) capacitance between Pin1 and Pin4. The measurement includes case parasitic capacitance.
- 6. Derived mathematically from one or more of the following directly measured parameters: f c, IL, 3 dB bandwidth, f_C versus T_C, and C₀.
- 7. The specifications of this device are based on the test circuit shown above and subject to change or obsolescence without notice.
- 8. Typically, equipment utilizing this device requires emissions testing and government approval, which is the responsibility of the equipment manufacturer.
- 9. Our liability is only assumed for the Surface Acoustic Wave (SAW) component(s) per se, not for applications, processes and circuits implemented within components or assemblies.

In keeping with our ongoing policy of product evolvement and improvement, the above specification is subject to change without notice.

ISO9001: 2000 Registered - Registration number 6830/2

For quotations or further information please contact us at: