

## LS3250SB NPN TRANSISTOR



## Linear Systems NPN Transistor

The LS3250SB is a NPN transistor mounted in a single SOT-23 package.

The 3 Pin SOT-23 provides ease of manufacturing, and a lower cost assembly option.

(See Packaging Information).

Low Output Capacitance

FEATURES							
LOW CAPACITANCE	≤ 2pF						
ABSOLUTE MAXIMUM RATINGS <sup>1</sup>							
@ 25°C (unless otherwise noted)							
Maximum Temperatures							
•							
Storage Temperature	-65°C to +150°C						
Operating Junction Temperature	-55°C to +150°C						
Maximum Power Dissipation							
Continuous Power Dissipation	TBD						
Maximum Currents							
Collector Current	50mA						
Maximum Voltages							
Collector to Collector Voltage	80V						

## ELECTRICAL CHARACTERISTICS @ 25°C (unless otherwise noted)

SYMBOL	CHARACTERISTICS	MIN.	TYP.	MAX.	UNITS	CONDITIONS
BV <sub>CBO</sub>	Collector to Base Voltage	40			V	I <sub>C</sub> = 10mA, I <sub>E</sub> = 0
$BV_{CEO}$	Collector to Emitter Voltage	40			V	$I_{C} = 10 \mu A, I_{B} = 0$
BV <sub>EBO</sub> <sup>2</sup>	Emitter-Base Breakdown Voltage	6.2			V	$I_{E} = 10 \mu A, I_{C} = 0$
		100				$I_C = 10 \mu A, V_{CE} = 5 V$
h <sub>FE</sub>	DC Current Gain	80				$I_C = 100 \mu A, V_{CE} = 5 V$
		80				$I_{C} = 1 \text{mA}, V_{CE} = 5 \text{V}$
V <sub>CE</sub> (SAT)	Collector Saturation Voltage			0.25	V	$I_{C} = 100 \text{mA}, I_{B} = 10 \text{mA}$
I <sub>EBO</sub>	Emitter Cutoff Current		-	0.2	nA	$I_{C} = 0A, V_{CB} = 3V$
I <sub>CBO</sub>	Collector Cutoff Current		-	0.2	nA	$I_{E} = 0A, V_{CB} = 20V$
C <sub>OBO</sub>	Output Capacitance			2	pF	$I_{E} = 0A, V_{CB} = 10V$
f <sub>T</sub>	Current <mark>Ga</mark> in Ba <mark>n</mark> dwidth Product		-	600	MHz	$I_C = 1 \text{mA}, V_{CE} = 5 \text{V}$
NF	Narrow Band Noise Figure			3	dB	$I_C = 100 \mu A$ , $V_{CE} = 5V$ , $BW = 200 Hz$ , $R_B = 10 \Omega$ ,
						f = 1KHz

## Notes

- 1. Absolute Maximum ratings are limiting values above which serviceability may be impaired
- 2. The reverse base-to-emitter voltage must never exceed 6.2 volts; the reverse base-to-emitter current must never exceed 10µA.



Available Packages:

LS3250SB in SOT-23 LS3250SB available as bare die

Please contact Micross for full package and die dimensions:

Email: <a href="mailto:chipcomponents@micross.com">chipcomponents@micross.com</a> Web: <a href="mailto:www.micross.com/distribution.aspx">www.micross.com/distribution.aspx</a> SOT-23 (Top View)

