

Dear customers,

## About the change in the name such as "Oki Electric Industry Co. Ltd." and "OKI" in documents to OKI Semiconductor Co., Ltd.

The semiconductor business of Oki Electric Industry Co., Ltd. was succeeded to OKI Semiconductor Co., Ltd. on October 1, 2008. Therefore, please accept that although the terms and marks of "Oki Electric Industry Co., Ltd.", "Oki Electric", and "OKI" remain in the documents, they all have been changed to "OKI Semiconductor Co., Ltd.". It is a change of the company name, the company trademark, and the logo, etc. , and NOT a content change in documents.

October 1, 2008 OKI Semiconductor Co., Ltd.

### OKI SEMICONDUCTOR CO., LTD.

550-1 Higashiasakawa-cho, Hachioji-shi, Tokyo 193-8550, Japan http://www.okisemi.com/en/



## Optical Components OF3647R

Rev. 8 [4. 2009]

### Preliminary

10Gbps APD with High Gain TIA receiver optical sub-assembly (ROSA)

#### **1. DESCRIPTION**

OF3647R is a high sensitivity APD-TIA receiver optical sub-assembly (ROSA). It includes a high speed InGaAs avalanche photodiode with a high gain TIA in a hermetically sealed coaxial package. It incorporates LC/SC receptacle and a flexible printed circuit (FPC). The signal GND and a receptacle are electrically isolated in this ROSA.

#### **2. FEATURES**

Power supply (TIA): 3.3VHigh sensitivity: -27.5dBm Typ. Differential transimpedance:  $12k\Omega$  Typ. Low power consumption: 0.1W Typ. Electrical isolation between signal GND and a receptacle Adjustable DC offset (Eye cross-point control) PKG outline compatible with XMD-MSA

#### **3. APPLICATION**

SONET /SDH GbE

(	2	0	
The	1		-
	- CAR		

#### 4.ABSOLUTE MAXIMUM RATING

		$(Tc = +25 \circ C, unless otherw$	wise specified)
Parameter	Symbol	Rating	Unit
APD Supply Voltage	VB	0 to VBR	V
TIA Supply Voltage	Vcc	0 to +3.7	V
DC Offset Adjustment Voltage	Vth	Vcc-1.0 to Vcc+0.5* <sup>1)</sup>	V
Vth Current	Ith	-1 to 1	mA
APD Reverse Current (cw)	IR	2	mA
Input Optical Power	Pin	+0	dBm
Operating Case Temparature	Tc	-5 to 85	°C
Storage Temparature	Tstg	-40 to 85	°C
Soldering Temperature		260 (10s)	°C

\*1) at all times including power up/down.

#### OF3647R

(Wavelength=1550nm, Tc =25°C, VCC=+3.3V, unless otherwise specified)						
Parameter	Symbol	Test Conditions	Min.	Тур.	Max.	Unit
Wavelength	λ	-	1250		1600	nm
APD Breakdown Voltage	VBR	ID=10µA	22	29	36	V
Temperature Coefficient of VBR	γ	-	0.03	0.05	0.07	V/°C
ADD Posnonsivity	RAPD	λ=1.55μm	0.7	0.8		A/W
ArD Responsivity		λ=1.31μm	0.7	0.8		
Dark Current	ID	VB=0.9xVBR			200	nA
Transimpedance	Zt	Pin= -27dBm Differential	10	12		kΩ
Bandwidth	BW	f-3dB, RL=50Ω M=9	6.0	8.0		GHz
Group Delay Deviation	GD	130MHz to 7.5GHz		±40		ps
Low Frequency Cutoff	$\mathbf{f}_{\mathrm{LOW}}$	f-3dB from 130MHz		45		kHz
Sensitivity	Prmin	9.95328Gbps, NRZ, BER=10 <sup>-12</sup> , PRBS2 <sup>31</sup> -1, Rext.=12dB, M=Mopt.		-27.5	-26.5	dBm
Overload	Prmax	9.95328Gbps, NRZ, BER=10 <sup>-12</sup> , PRBS2 <sup>31</sup> -1 M=Mopt.	-6	-3		dBm
Maximum Output Swing	Vout	Differential		450	650	mV
Supply Current	Icc	-		32		mA
Recommended TIA Supply Voltage	Vcc	-	+3.1	+3.3	+3.5	V
Output Return Loss	ERL	130MHz to 7.5GHz Differential S22			-8	dB
Optical Return Loss	ORL	-			-27	dB
Thermistor Resistance	Rth	Tthermistor=25°C	9.5	10	10.5	kΩ
Thermistor B Constant	В	Tc= $+25$ to $+50^{\circ}$ C	3800	3900	4000	K

#### 5.0PTICAL AND ELECTRICAL CHARACTERISTICS

#### 6. CONNECTOR AND FIBER SPECIFICATIONS OF3647R-LC-x (LC receptacle)

Parameter	Specifications	Unit
Applicable Optical Fiber	C-SMF	
Core Diameter	9.5	um
Cladding Diameter	125	um
Ferrule Diameter	1.25	mm

#### OF3647R-SC-x (SC receptacle)

Parameter	Specifications	Unit
Applicable Optical Fiber	C-SMF	
Core Diameter	9.5	um
Cladding Diameter	125	um
Ferrule Diameter	2.5	mm

#### OF3647R



#### 7. OUTLINE DRAWING All dimensions in millimeters(Unit: mm) OF3647R-LC-x (LC receptacle)

#### OF3647R-SC-x (SC receptacle)





5.6

#### OF3647R



#### <u>Note (\*)</u>

When using without DC offset control, Vth terminal should be **NO CONNECTION**. And also, please make sure Vth voltage NOT to go to GND level during power-on or power-off transitions and after power on.

# 9. ORDERING INFORMATION OF3647R - -

Recptacle Type LC : LC SC : SC Assignment of Vth terminal #7 : B Not assigned : C

#### SAFETY AND HANDRING INFORMATION ON THIS PRODUCT

Caution	The product contains gallium arsenide, GaAs.
	GaAs vapor and powder are hazardous to human health if inhaled, ingested or swallowed.
GaAs Product	Do not destory or burn the product.
	Do not crush or chemically dissolve the product.
	Do not put the product in the mouth.
	Observe related laws and company regulations when discarding this product.
	The product should be excluded from general industrial waste or household garbage.
Caution	A glass-fiber is attached on the product. Handle with care.
Optical Fiber	When the fiber is broken or damaged, handle carefully to avoid injury from
-	the damaged part or fragments.
Attention	Appropriate precautions must be taken to aviod exposure to ESD and EOS during handring the
ESD sensitive	product.

#### OKI SEMICONDUCTOR CO., LTD.

#### **Notice**

- 1. The information contained herein can change without notice owing to product and/or technical improvements. Before using the product, please make sure that the information being referred to is up-to-date.
- 2. The outline of action and examples for application circuits described herein have been chosen as an explanation for the standard action and performance of the product. When planning to use the product, please ensure that the external conditions are reflected in the actual circuit, assembly, and program designs.
- 3. When designing your product, please use our product below the specified maximum ratings and within the specified operating ranges including, but not limited to, operating voltage, power dissipation, and operating temperature.
- 4. OKI SEMICONDUCTOR assumes no responsibility or liability whatsoever for any failure or unusual or unexpected operation resulting from misuse, neglect, improper installation, repair, alteration or accident, improper handling, or unusual physical or electrical stress including, but not limited to, exposure to parameters beyond the specified maximum ratings or operation outside the specified operating range.
- 5. Neither indemnity against nor license of a third party's industrial and intellectual property right, etc. is granted by us in connection with the use of the product and/or the information and drawings contained herein. No responsibility is assumed by us for any infringement of a third party's right which may result from the use thereof.
- 6. The products listed in this document are intended for use in general electronics equipment for commercial applications (e.g., office automation, communication equipment, measurement equipment, consumer electronics, etc.). These products are not authorized for use in any system or application that requires special or enhanced quality and reliability characteristics nor in any system or application where the failure of such system or application may result in the loss or damage of property, or death or injury to humans. Such applications include, but are not limited to, traffic and automotive equipment, safety devices, aerospace equipment, nuclear power control, medical equipment, and life-support systems.
- 7. Certain products in this document may need government approval before they can be exported to particular countries. The purchaser assumes the responsibility of determining the legality of export of these products and will take appropriate and necessary steps at their own expense for these.
- 8. No part of the contents contained herein may be reprinted or reproduced without our prior permission. **Copyright 2009 OKI SEMICONDUCTOR CO., LTD.**