
DF2005S thru DF210S

SURFACE MOUNT GLASS PASSIVATED BRIDGE RECTIFIERS SINGLE-PHASE GLASS BRIDGE

REVERSE VOLTAGE - 50 TO 1000 VOLTS FORWARD CURRENT - 2.0 AMPERES





Dimensions in inches and (millimeters)

FEATURES

- Rating to 1000V PRV
- · Ldeal for printed circuit board
- · Low forward voltage drop, high current capability
- Reliable low cost construction utilizing molded Plastic technique results in inexpensive product
- Lead in plated copper
- The plastic material has UL flammability Classification 94V-0

MECHANICAL DATA

Polarity: As marked on body Weight: 0.02 ounce, 0.38gram Mounting position: Any

MAXIMUM RATIXGS AND ELECTRICAL CHARACTERISTICS

Ratings at 25°C ambient temp. unless otherwise specified Single phase, half sine wave, 60Hz, resistive or inductive load For capacitive load, derate current by 20%

		DF 2005S	DF 201S	DF 202S	DF 204S	DF 206S	DF 208S	DF 210S	UNITS
Maximum Recurrent Peak Reverse Voltage	Vrrm	50	100	200	400	600	800	1000	Volts
Maximum RMS Bridge input Voltage	VRMS	35	70	140	280	420	560	700	Volts
Maximum DC Blocking Voltage	V _{DC}	50	100	200	400	600	800	1000	Volts
Maximum Average Forward Rectified Current @ $T_A=40^{\circ}C$	(AV)	2.0						Amps	
Peak Forward Surge Current, 8.3ms Single Half Sine-Wave Superimposed on Rated Load (JEDEC Method)	lfsm	60							Amps
Maximum Forward Voltage at 2.0A DC	VF	1.1						Volts	
Maximum DC Reverse @T _J =25°C at rated DC Blocking Voltage @T _J =125°C	IR	10 500							μΑ
I ² t Rating for fusing (t<8.3ms)	l ² t	10.4						A ² S	
Typical Junction capacitance per element (Note 1)	Cı	25							рF
Typical Thermal resistance (Note 2)	R ⊕ JA	40							°C / W
Operating Temperature Range	LΤ	-55 to +150							°C
Storage Temperature Range	Tstg	-55 to +150						°C	

NOTES:

- 1. Measured at 1.0 MHz and Applied Reverse Voltage of 4.0 Volts DC $\,$
- 2. Thermal Resestance From Junction to Ambient and from junction to lead mounted on P.C.B with 0.5 x 0.5" (13x13mm) copper pads.



DF2005S thru DF210S

SURFACE MOUNT GLASS PASSIVATED BRIDGE RECTIFIERS SINGLE-PHASE GLASS BRIDGE

REVERSE VOLTAGE - 50 TO 1000 VOLTS FORWARD CURRENT - 2.0 AMPERES

