

SMC770

TECHNICAL DATA

Visible LED, SMD

SMC770 is a AlGaAs LED mounted on a ceramic SMD package and sealed with silicone or epoxy resin for damp proof. On forward bias, it emits a radiation of typical 10 mW at a peak wavelength of 770 nm.

Specifications

- Structure: AlGaAs
- Peak Wavelength: typ. 770 nm
- Optical Output Power: typ. 10 mW
- Package: Ceramic SMD, silicon/epoxy resin

Absolute Maximum Ratings (T_a=25°C)

Item	Symbol	Value	Unit
Power Dissipation	PD	190	mW
Forward Current	l _F	100	mA
Pulse Forward Current**	I _{FP}	500	mA
Reverse Voltage	V _R	5	V
Operating Temperature	T _{opr}	-20 +80	°C
Storage Temperature	T _{stg}	-30 +80	°C
Soldering Temperature *	T _{sol}	240	°C

* must be completed within 5 seconds

** max duty cycle 1%, max puls width 10µs

Electro-Optical Characteristics

ltem	Symbol	Condition	Min.	Тур.	Max.	Unit
Forward Voltage	V _F	l _F = 50 mA	-	1.75	1.95	V
Reverse Current	I _R	$V_R = 5 V$	-	-	10	μA
Total Radiated Power*	Po	l _F = 50 mA	5.0	10.0	-	mW
Radiation Intensity	Ι _Ε	l _F = 50 mA	2.0	5.0	-	mW/sr
Peak Wavelength	λ_{P}	l _F = 50 mA	755	770	785	nm
Half Width	Δλ	l _F = 50 mA	-	30	-	nm
Viewing Half Angle	Θ _{1/2}	l _F = 50 mA	-	±55	-	deg.
Rise Time	t _R	l _F = 50 mA		80		ns
Fall Time	t _F	$I_F = 50 \text{ mA}$		80		ns

* Total Radiated Power is measured by Photodyne #500

Notes

- Do not view directly into the emitting area of the LED during operation!
- The above specifications are for reference purpose only and subjected to change without prior notice.





(Unit: mm)

AlGaAs



Soldering Conditions

- DO NOT apply any stress to the lead particularly when heat.
- After soldering the LEDs should be protected from mechanical shock or vibration until the LEDs return to room temperature.
- When it is necessary to clamp the LEDs to prevent soldering failure, it is important to minimize the mechanical stress on the LEDs.



Temperature Profile

PCB Footprint Layout



Static Electricity

- LEDs are very sensitive to Static Electricity and surge voltage. It is recommended to always wear a wrist band or an anti-electrostatic glove when handling the LEDs.
- All devices, equipment and machinery must be grounded properly. It is recommended that precautions should be taken against surge voltage to the equipment that mounts the LEDs.