 For reference
For Approval

(1/8)

Spec. No.: OMI-G5SB-03006 A

Date of issue:

Nov. 7 '03



Issued by	Checked by	Approved by
mobile	Month	L
Sarjoko	Sujatmoko	Isman N.

PT. OMRON MANUFACTURING OF INDONESIA

<u> </u>	-	uct specification sheets. like you to return a copy to our side. ( Closing da	atem di <b>)</b>
SPECIFICATION	:	5,9,12 & 24VDC	
TYPE	:	G5SB-1A4	
PRODUCT NAME	:	PCB POWER RELAY	
CUSTOMER	:		

Receipt Conf	Receipt Confirmation and / Approval  Sales ) (Filled by End Customer)								
( Filled by Sales )									
	·								

Distribution	No. of copies	Rev.	Date of revision	Revision contents							
(Sales)											
(Customer)											

OMRON

The units and figures in brackets { } are for	or reference only	
	. [7].	o.: OMI-G5SB-03006 A (2 / 8)
1. Type  2. Structure  Optional items are indicated by a check management of the control of the		VER RELAY
2.1. Outline drawing	Drawing No.:	0414015
2.2. Structure drawing	Drawing No.:	0414018
2.3. Contact structure		1A
2.4. Contact mechanism	Sin	gle Contact
2.5. Contact material	Surface material	Base material Ag alloy
2.6. Protective structure	√ Plastic sealed ☐ Fi	ux protection
3. Standards	·	
3.1. Authorized specifications	UL,	CSA, VDE
3.2. Applicable specifications	UL 508 CSA (C22.2 No. 14) IEC (255), VDE0435	File No. E41515 File No. LR31928 File No. 40003957
3.3. Conforming specifications	Electrical appliance and	material control law of JAPAN
4. Ratings		
4.1. Operating coil (1) Rated voltage & frequency	√ Refer to table 1.	(Initial values)
(2) Rated current	Setting current	mA ±10% ( at V Hz)
(3) Coil resistance	Resetting current Setting resistance	
(4) Rated power consumption	Resetting resistance Approx. 400 mW	%
(5) Allowable range of voltage fluc	tuation: <u>90</u> to	110% of the rated voltage
4.2 Switching section		

(1) Rated load Resistive load 250

Resistive load 250VAC 5A (NO) 125VAC 3A (NO) 30VDC 5A (NO) 227 VAC 2A (No)

50K ops 200K ops 100K ops

200 K ops

( Optional items are indicated by a check mark.	√ ) No. : OMI-G5SB-03006 A (3 / 8)
<ul><li>(2) Rated current</li><li>(3) Maximum contact voltage</li><li>(4) Maximum contact current</li></ul>	5_A <sub>2</sub> A} AC_250 V DC_30_V Resistive load
	AC <u>5</u> A DC <u>5</u> A Inductive load AC <u>— A (P.f. = _ — )</u>
(5) Maximum switching capacity	C
(6) Minimum applicable load	DC W (L/R=ms) DC5
5. Performance ( Initial values )	( $\lambda$ 60 = 0.1 x 10 <sup>-6</sup> ) (Switching frequency:
,	A Section of the sect
5.1. Contact resistance	
5.2. Operate voltage	☐ Setting voltageV max.  V Refer to Table 1.
5.3. Release voltage	Resetting voltageV min.
5.4. Operate time	✓ Setting time 10 ms max. (operated with rated voltage)
5.5. Release time	Resetting time 5 ms max. (operated with rated voltage)
<ul> <li>5.6. Insulation resistance</li> <li>(1) Between coil and contacts.</li> <li>(2) Between contacts of opposite poils.</li> <li>(3) Between contacts of the same poils.</li> <li>(4) Between set coil and reset coil.</li> <li>(5) Between coil / contact terminals non - charged metallic section (</li> </ul>	oolarity 1,000 Megaohm min.  — Megaohm min.  and exposed — Megaohm min.

(2) Malfunction

√ Set status
(When

Contacts must not open for  $_{1}$  ms or longer after the relay is subjected to a shock of  $_{100}$  m/s<sup>2</sup> in each direction for  $_{3}$  times.

Energized)

Contacts must not open for \_\_\_\_ ms or longer after the relay is subjected to a shock of \_\_\_\_ m/s² in each direction for \_\_\_\_ times.

(When not Energized)

Reset status

5.11. Terminal strength

When stress force of 1 kgf { 9.8 N } is applied in the direction of the vertical axis for 10 seconds, there shall be no abnormality.

Must be free from any abnormality after a bend stress of ± 45° angle is applied to the terminal in a round trip. However, dimensional deformation of terminal caused by the force shall not be considered mechanical

damage.

## 7.

- (2) The storage site shall have no visible dust.
- (3) Products shall not be exposed to direct sunlight.
- (4) No force or stress that can cause dimensional deformation or quality deterioration shall be applied.

8.	Operating conditions:	Pro	ducts sh	all be u	sed und	der the	e folic	owing con	ditions	:			
8.1.	Temperature	✓	-40	to	70	_°C	$\square$		to		_°C		
		There shall be no ice formation or dew condensation.											

No.: OMI-G5SB-03006 A (6 / 8)

8.2. Humidity

5 to 95 %RH

8.3. Mounting direction

Free

- 8.4. Environments
  - (1) Products shall not be used in a place exposed to corrosive gases such a hydrogen sulfide gas or air containing salt.
  - (2) There shall be no visible dust.
  - (3) Products shall not be exposed to direct sunlight.
  - (4) No force or stress that can caused dimensional deformation or quality deterioration shall be applied.

9. Table 1 (Coil Ratings)

 <del>5.5 . ( \$5.</del>						
Rated	Rated	Coil	Operate	Release	Permissible	Power
Voltage	Current Resistance		Voltage	Voltage	Voltage	Consumption
(V)	(mA)	$(\Omega)$	%	of Rated Volta	(mW)	
5	80	62.5				
9	44.4	202.5	75 Max.	5 Min.	90 ~ 110	400 Approx.
12	33.3	360	75 IVIAN.	J WIIII.	90 ~ 110	400 Applox.
24	16.7	1440				

10. Change of indications


Specification other than the ratings, performance, structure and external dimensions and mounting dimension are subject to change.

- 11. Validity of specification sheet
  - 11.1 When no confirmation is received within one year of the issuing date of this specification sheet, this specification sheet will be invalidated.
  - 11.2 This specification sheet is valid for 3 years after the date of receiving confirmation
- 12. Warranty period
  - 12.1 Warranty period is one year from the date on which the products are delivered to the location designated by the customer.
  - 12.2 Scope of warranty

The warranty is limited only to repairs or replacement of defective parts, when Omron is responsible for the malfunctioning or defect that occurs during the warranty period.

The warranty applies only to individual products delivered by Omron. Therefore, the warranty does not cover any other damages induced by the malfunctioning of Omron products.

13. Marking of relay



Note: For DC9V, VDE still in progress
VDE logo will be put after get approval.


CONTROLLED COR

08 NOV-2003

O M I

14. Handling cautions

- 14.1 Do not use ultrasonic cleaning, since it causes resonance inside the relay and can result in coil disconnection and contact sticking.
- 14.2 Do not drop products to avoid deterioration of the initial performance.



									<u>.</u>		· · · · · · · · · · · · · · · · · · ·				• •	NO. :										8 / 8)
	1	<b>⋖</b>	T.		_1	<del></del>	<del>-</del>	ם	0			1	-	· · · · · · · · · · · · · · · · · · ·	ပ				1			c				27411
Σ'n	-	_	-		-	-	-	, errej.	*2# #F	*···	-	* Spran		77	-		·æ	1		OTY.		s. Jeg	١ ,	Ž. A.		<u>इ</u>
MATERIAL NAME	POLYBUTYLENE TEREPHTHALATE	POLYBUTYLENE TEREPHTHALATE	POLYBUTYLENE TEREPHTHALATE	POLYBUTYLENE TEREPHTHALATE	SOFT MAGNETIC IRON PLATE	SOFT MAGNETIC IRON PLATE	SOFT MAGNETIC IRON BAR	COPPER ALLOY	COPPER ALLOY	COPPERALLOY	SILVER ALLOY	SILVER ALLOY	COPPER ALLOY	POLYURETHANE COPPER WIRE	EPOXY RESIN	and the second s					CECB_1///4/		KUCLURE URAWING	0414018	ED FOR 65SB-1A	Poper use (O)
PARTS NAME	BASE	CASE	SPOOL	CARD	YOKE	ARMATURE	00 00 00 00 00 00 00 00 00 00 00 00 00	HINGE SPRING	MOV TERMINAL C	STA. TERMINAL A	MDV, CONTACT C	STA, CONTACT A	TERMINAL COIL	MAGNET WIRE	SEAL		3	(a 141)	**		SCALE		85 5	調を人をう		
ž	14	~	m	4	'n	۰,	-	60	٩	2	F	건	<u>a</u>	2	2									L.	Tar and	
	5				C			The second secon						نگر دورون	$\langle$				(zs)		MATERIAL		CES DESIGNED	ELA SPECIPIED	/C NO. SIGN / Sept.18,2001 Sept.27,2001	Поящо
		The side of the state of the st	t too service to	MNV 2003	Province of the second	- CONTROL STATE								(2)	(F									New OM Drawing	E/C CONTENTS	© CMRON Corporation 1998 All Rights Reserved.
	PARTS NAME MATERIAL NAME	BASE POLYBUTYLENE TEREPHTHALATE	No Parts name Material Name Offy 1 Base Polybutylene Terephthalate 1 2 Case Polybutylene Terephthalate 1	No Parts name Material Name 1 Base Polybutylene terephthalate 2 Case Polybutylene terephthalate 3 SPOOL POLYBUTYLENE TEREPHTHALATE	No Parts name Haterial name Otty 1 Base Polybutylene terephthalate 1 2 Case Polybutylene terephthalate 1 3 SPOOL POLYBUTYLENE TEREPHTHALATE 1 4 CARD POLYBUTYLENE TEREPHTHALATE 1	No         PARTS: NAME         MATERIAL NAME         QTY           1         BASE         POLYBUTYLENE TEREPHTHALATE         1           2         CASE         POLYBUTYLENE TEREPHTHALATE         1           3         SPOOL         POLYBUTYLENE TEREPHTHALATE         1           4         CARD         POLYBUTYLENE TEREPHTHALATE         1           4         CARD         POLYBUTYLENE TEREPHTHALATE         1           5         YOKE         SOFT MAGNETIC IRON PLATE         1	No Parts Name	No Parts: Name	NA PARTS NAME   MATERIAL NAME   DTY   BASE   POLYBUTYLENE TEREPHTHALATE   1     2   CASE   POLYBUTYLENE TEREPHTHALATE   1     3   SPOOL   POLYBUTYLENE TEREPHTHALATE   1     4   CARD   POLYBUTYLENE TEREPHTHALATE   1     5   YÖKE   SOFT MAGNETIC IRON PLATE   1     6   ARMATURE   SOFT MAGNETIC IRON PLATE   1     7   CORE   SOFT MAGNETIC IRON PLATE   1     8   MINGE SPRING   COPPER ALLOY   3	1 BASE   POLYBUTYLENE TEREPHTHALATE   1     2 CASE   POLYBUTYLENE TEREPHTHALATE   1     3 SPOOL   POLYBUTYLENE TEREPHTHALATE   1     4 CARD   POLYBUTYLENE TEREPHTHALATE   1     5 YOKE   SOFT MAGNETIC IRON PLATE   1     6 ARMATURE   SOFT MAGNETIC IRON PLATE   1     7 CORE   SOFT MAGNETIC IRON PLATE   1     8 HINGE SPRING   COPPER ALLOY   1     9 MOV. TERMINAL C COPPER ALLOY   1     1	No Parts name	1 8ASE   POLYBUTYLENE TEREPHTHALATE   1     2 CASE   POLYBUTYLENE TEREPHTHALATE   1     3 SPOOL   POLYBUTYLENE TEREPHTHALATE   1     4 CARD   POLYBUTYLENE TEREPHTHALATE   1     5 YOKE   SOFT MAGNETIC IRON PLATE   1     6 ARMATURE   SOFT MAGNETIC IRON PLATE   1     7 CORE   SOFT MAGNETIC IRON PLATE   1     8 HINGE SPRING   COPPER ALLOY   1     1 MOY. CONTROL SILVER ALLOY   1     1 MOY.	1 BASE   POLYBUTYLENE TEREPHTHALATE   1 BASE   POLYBUTYLENE TEREPHTHALATE   1     2 CASE   POLYBUTYLENE TEREPHTHALATE   1     3 SPOOL   POLYBUTYLENE TEREPHTHALATE   1     4 CARD   POLYBUTYLENE TEREPHTHALATE   1     5 YOKE   SOFT MAGNETIC IRON PLATE   1     7 CORE   SOFT MAGNETIC IRON PLATE   1     1	1   BASE   POLYBUTYLENE TEREPHTHALATE   1	1 BASE   POLYBUTYLENE TEREPHTHALATE   1 BASE   POLYBUTYLENE TEREPHTHALATE   1   1   1   1   1   1   1   1   1	1   BASE   POLYBUTYLENE TEREPHTHALATE   1	1   9ASE   POLYBUTYLENE TERPHTHALATE   1	1 8ASE   POLYBUTYLENE TERPHTHALATE   1 8ASE   POLYBUTYLENE TERPHTHALATE   1   1   1   1   1   1   1   1   1	1   BASE   POLYBUTYLENE TEREPHTHALATE   1     2   CASE   POLYBUTYLENE TEREPHTHALATE   1     3   SPO3L   POLYBUTYLENE TEREPHTHALATE   1     4   CARD   POLYBUTYLENE TEREPHTHALATE   1     5   YOKE   SOFT MAGNETIC RON PLATE   1     6   ARMATURE   SOFT MAGNETIC RON PLATE   1     7   CORE   SOFT MAGNETIC RON PLATE   1     8   MINGE SPRING   COPPER ALLOY   1   1     9   4   8   S   S   S   S   S   S   TRRININAL A   COPPER ALLOY   1   1     10   STA. TERMINAL C   COPPER ALLOY   1   1     11   NOV. CONTACT S ISLUER ALLOY   1   1     12   STA. CONTACT S ISLUER ALLOY   1   1     13   TERPHNAL COLL   COPPER ALLOY   1   1     14   MAGNET WIRE   POLYMERTHANE COPPER WIRE   3     15   SEAL   EPOXY RESIN   1   1     16   STA. TERMINAL COLL   COPPER ALLOY   1   1     17   STA. CONTACT S ISLUER RALOY   1   1     18   SEAL   EPOXY RESIN   1   1     19   STA. TERMINAL COLL   COPPER ALLOY   1   1     19   STA. TERMINAL COLL   COPPER ALLOY   1   1     19   STA. TERMINAL COLL   COPPER ALLOY   1   1     10   STA. TERMINAL COLL   COPPER ALLOY   1   1     11   STA. CONTACT S ISLUER RALOY   1   1     12   STA. CONTACT S ISLUER RALOY   1   1     14   MAGNET WIRE   POLYMETHANE COPPER WIRE   3     15   SEAL   EPOXY RESIN   1   1     16   STA. TERMINAL COLL   COPPER ALLOY   1   1     17   STA. TERMINAL COLL   COPPER ALLOY   1   1     18   SEAL   EPOXY RESIN   1   1     19   TERMINAL COLL   COPPER ALLOY   1   1     10   STA. TERMINAL COLL   COPPER ALLOY   1   1     11   STA. TERMINAL COLL   COPPER ALLOY   1   1     12   STA. TERMINAL COLL   COPPER ALLOY   1   1     13   TERMINAL COLL   COPPER ALLOY   1   1     14   TERMINAL COLL   COPPER ALLOY   1   1     15   STA. TERMINAL COLL   COPPER ALLOY   1   1     15   STA. TERMINAL COLL   COPPER ALLOY   1   1     15   STA. TERMINAL COLL   COPPER ALLOY   1   1     17   STA. TERMINAL COLL   COPPER ALLOY   1   1     18   STA. TERMINAL COLL   COPPER ALLOY   1   1     19   STA. TERMINAL COLL   COPPER ALLOY   1   1     10   STA. TERMINAL COLL   COPPER ALLOY   1   1     10   STA. TERMINAL COLL   COPPER ALL	1   BASE   POLYBUTYLEME TEREPHTHALATE   1	1 8ASE   POLYBUTYLENE TEREPHTHALATE   1 8ASE   POLYBUTYLENE TEREPHTHALATE   1 8ASE   POLYBUTYLENE TEREPHTHALATE   1 8 SPOOL   POLYBUTYLENE TEREPHTHALATE   1 8 SPOOL   POLYBUTYLENE TEREPHTHALATE   1 8 SPOOL   POLYBUTYLENE TEREPHTHALATE   1 1 CORE   SOFT MAGNETIC BION PLATE   1 1 MOV. CONTACT   SILVER ALLOY   1 1 MOV. CONTACT   SILV	1 BASE   POLYBLYLEK TEREPHTHALATE   1 BASE   POLYBLYLEK TEREPHTHALE COPPER WINTE   1 BASE   POLYBLYLEK TEREPHTHALE COPPER TEREPHTHALE C	19 ASE   POLYBUTYLEN TEREPHTHALATE   1	10 ASE   POLYBOTYCENE TEREPHTHALATE   1 ASE   POLYBOTYCENE   1 ASE   POLYBOTYCE COPPERATION   1 ASE   POLYBOTYCENE   1 ASE   POLYBOTYCE   POLYBOTYCE	1	1    545E

## **Mouser Electronics**

**Authorized Distributor** 

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

## Omron:

G5SB-1A4-DC5 G5SB-1A4-DC12