

# E Cores (9498103002)



Part Number: 9498103002

98 E CORE SET

**The E core geometry offers an economical design approach for inductive applications in a variety of power designs.**

E cores can be supplied with the center post gapped to a mechanical dimension or an  $A_L$  value.

[Catalog Drawing](#)  
[3D Model](#)

Weight indicated is per pair or set.

Weight: 4.6 (g)

Dim	mm	mm tol	nominal inch	inch misc.
A	19	±0.40	0.748	—
B	8	±0.30	0.315	—
C	4.8	±0.30	0.189	—
D	5.75	±0.25	0.226	—
E	13.8	min	0.543	min
F	4.5	±0.30	0.177	—



### Chart Legend

$\Sigma l / A$  : Core Constant,  $l_e$  : Effective Path Length,  $A_e$  : Effective Cross- Sectional Area,  $V_e$  : Effective Core Volume

$A_L$  : Inductance Factor 

Explanation of Part Numbers: Digits 1 & 2 = product class and 3 & 4 = material grade.

Electrical Properties	
$A_L$ (nH)	1200 ±25%
$A_e$ (cm <sup>2</sup> )	0.22
$\Sigma l / A$ (cm <sup>-1</sup> )	18.1
$l_e$ (cm)	3.99
$V_e$ (cm <sup>3</sup> )	0.878
$A_{min}$ (cm <sup>2</sup> )	0.216