

Silicon Medium Barrier Schottky Diodes

M/A-COM Products Rev. V8

Features

- RF & Microwave Medium Barrier Silicon 70 V Schottky Diode
- Available as Single Diode, Series Pair or Unconnected Pair Configurations.
- Low Profile Surface Mount Plastic Package
- Lead Free (RoHS Compliant) Equivalents Available With 260 Deg. C Reflow Capability

Description and Applications


The MA4E1340 series is a silicon medium barrier schottky diode suitable for use in mixer, detector and limiter circuits. These diodes are also suitable for usage in anti-parallel, shunt power protection circuits for 50 Ω and 75 Ω systems.

These parts are offered with Sn/Pb plating, as well as with 100 % matte Sn plating on the RoHS compliant part numbers.

The MA4E1340 Series of Schottky diodes is available in the SOT-23 (case style 287), SOT-143 (case style 1068), SOT-323 (case style 1146) and the SOD 323, (case style 1141) plastic package. These packages are supplied on tape and reel for automatic pick and place assembly and for surface mount placement to circuit boards, as indicated by a "T" to the P/N suffix.

These Silicon Medium Barrier, 70 V Schottky Diodes are Useful in Detector, Limiter, Mixer, and Surge Protection Applications for Operating Frequency Bands from DC through 6 GHz.

Package Outlines




[•] India Tel: +91.80.4155721 • China Tel: +86.21.2407.1588 Visit www.macomtech.com for additional data sheets and product information.





Silicon Medium Barrier Schottky Diodes

M/A-COM Products Rev. V8


Configurations (Top View)








Series Pair MA4E1340B-287T MA4E1340B-1146T



Single MA4E1340A1-1141T MADS-001340-1279OT



Unconnected Pair MA4E1340E-1068T

Standard Part Numbers and RoHS Equivalents

| Standard Part Number | RoHS Compliant Part Number | Package Style |
|----------------------|----------------------------|---------------|
| MA4E1340A-287T | MA4E1340A1-287T | SOT-23 |
| MA4E1340A-1146T | MA4E1340A1-1146T | SOT-323 |
| MA4E1340B-287T | MA4E1340B1-287T | SOT-23 |
| MA4E1340B-1146T | MA4E1340B1-1146T | SOT-323 |
| N/A | MA4E1340A1-1141T | SOD-323 |
| N/A | MADS-001340-1279OT | SC-79 |
| MA4E1340E-1068T | MA4E1340E1-1068T | SOT-143 |

[•] India Tel: +91.80.4155721 • China Tel: +86.21.2407.1588 Visit www.macomtech.com for additional data sheets and product information.



Silicon Medium Barrier Schottky Diodes

M/A-COM Products Rev. V8

Maximum Ratings @ 25 °C (unless otherwise specified) 1

| Parameter | Unit | Values |
|--|------|-------------|
| Operating Temperature | °C | -55 to +125 |
| Storage Temperature | °C | -55 to +125 |
| Total Power Dissipation (RF and D.C.) | mW | 250 |
| Continuous Forward Current | mA | 15 |
| Surge Forward Current, @ t < 10 millisec | mA | 100 |
| Reverse Voltage | Vb | 70 |
| Soldering Temperature (Standard Part #) | °C | +235 |
| Soldering Temperature (RoHS Compliant Part #) | °C | +260 |

^{1.} Please refer to Application Note M538 for surface mounting instructions

Electrical Specifications @ $T_A = +25$ °C

| Parameter | Condition | Symbol | Specification |
|---------------------------|--------------------------|----------------|--|
| Forward Voltage | I _F = 1 mA | V_{F} | 410 mV max. |
| Delta Forward Voltage | I _F = 1 mA | ΔV_F | 20 mV max. For series pair and unconnected pair configurations |
| Forward Voltage | I _F = 15 mA | V_{F} | 1.0 V max. |
| Total Capacitance | $V_R = 0 V$ F = 1 MHz | Ст | 1.5 pF max. |
| Reverse Leakage Current | V _R = 50 V | I _R | 200 nA max. |
| Reverse Voltage Breakdown | I _R = 10 μA | Vb | 70 V min. |

[•] India Tel: +91.80.4155721 Visit www.macomtech.com for additional data sheets and product information.

[•] China Tel: +86.21.2407.1588




Silicon Medium Barrier Schottky Diodes


M/A-COM Products Rev. V8

Circuit Models


SOT-23




SOT-143



SOT-323



SOD-323



India Tel: +91.80.4155721
 China Tel: +86.21.2407.1588
 Visit www.macomtech.com for additional data sheets and product information.




Silicon Medium Barrier Schottky Diodes

M/A-COM Products Rev. V8

Case Styles

SOT-23




SOT-23 (Case Style 287)

| | INCHES | | MILLIM | ETERS |
|------|---------------|-------|--------------|--------|
| DIM. | MIN. | MAX. | MIN. | MAX. |
| Α | | 0.048 | _ | 1.22 |
| В | | 0.008 | _ | 0.20 |
| С | - | 0.040 | _ | 1.00 |
| D | 0.013 | 0.020 | 0.35 | 0.50 |
| Е | 0.003 | 0.006 | 0.08 | 0.15 |
| F | 0.110 | 0.119 | 2.80 | 3.00 |
| G | 0.047 | 0.056 | 1.20 | 1.40 |
| Н | 0.037 typical | | 0.95 typical | |
| J | 0.075 typical | | 1.90 t | ypical |
| K | | 0.103 | _ | 2.60 |
| L | | 0.024 | _ | 0.60 |
| DIM. | GRADIENT | | | |
| М | 10° max.2 | | | |
| N | 2°30° | | | |

2. Applicable on all sides

SOT-143



SOT-143 (Case Style 1068)

| | INCHES | | MILLIMI | ETERS |
|------|-----------------------|-------|--------------|-------|
| DIM. | MIN. | MAX. | MIN. | MAX. |
| Α | - | 0.044 | - | 1.10 |
| В | - | 0.004 | - | 0.10 |
| С | - | 0.040 | - | 1.00 |
| D | 0.013 | 0.020 | 0.35 | 0.50 |
| Е | 0.030 | 0.035 | 0.75 | 0.90 |
| F | 0.003 | 0.006 | 0.08 | 0.15 |
| G | 0.110 | 0.119 | 2.80 | 3.00 |
| Н | 0.047 | 0.056 | 1.20 | 1.40 |
| J | 0.075 typical | | 1.90 ty | pical |
| K | 0.075 typical | | 1.90 typical | |
| L | - | 0.103 | - | 2.6 |
| M | = | 0.024 | - | 0.6 |
| DIM. | GRADIENT | | | |
| N | 10° max. ³ | | | |
| Р | 2° 30° | | | |

3. Applicable on all sides

[•] North America Tel: 800.366.2266 • Europe Tel: +353.21.244.6400

[•] India Tel: +91.80.4155721 • China Tel: +86.21.2407.1588 Visit www.macomtech.com for additional data sheets and product information.




Silicon Medium Barrier Schottky Diodes

M/A-COM Products Rev. V8

Case Styles (Cont'd)


SOT-323



SOT-323 (Case Style 1146)

| | INCHES | | MILLIM | ETERS |
|------|--------|-------|--------|-------|
| DIM. | MIN. | MAX. | MIN. | MAX. |
| Α | 0.063 | 0.087 | 1.6 | 2.2 |
| В | 0.045 | 0.053 | 1.15 | 1.35 |
| С | 0.079 | 0.087 | 2.0 | 2.2 |
| D | 0.047 | 0.055 | 1.2 | 1.4 |
| Е | 0.008 | 0.016 | 0.2 | 0.4 |
| F | 0.031 | 0.039 | 0.8 | 1.0 |
| G | - | 0.004 | _ | 0.1 |
| Н | 0.003 | 0.006 | 0.08 | 0.15 |
| J | 0.004 | 0.010 | 0.1 | 0.25 |

SOD-323



SOD-323 (Case Style 1141)

| | INCHES | | MILLIM | ETERS |
|------|--------|-------|--------|-------|
| DIM. | MIN. | MAX. | MIN. | MAX. |
| Α | - | 0.043 | İ | 1.1 |
| В | ı | 0.004 | 1 | 0.1 |
| С | _ | 0.008 | 1 | 0.2 |
| D | 0.010 | 0.016 | 0.25 | 0.4 |
| Е | 0.003 | 0.006 | 0.08 | 0.15 |
| F | 0.063 | 0.075 | 1.6 | 1.9 |
| G | 0.045 | 0.057 | 1.15 | 1.45 |
| H | 0.091 | 0.106 | 2.3 | 2.7 |

changes to the product(s) or information contained herein without notice.

[•] India Tel: +91.80.4155721 Visit www.macomtech.com for additional data sheets and product information.

[•] China Tel: +86.21.2407.1588




Silicon Medium Barrier Schottky Diodes

M/A-COM Products Rev. V8

Case Styles (Cont'd)

ODS-1279



[•] India Tel: +91.80.4155721 Visit www.macomtech.com for additional data sheets and product information.

[•] China Tel: +86.21.2407.1588