

# MOS FIELD EFFECT TRANSISTOR **3SK231**


## RF AMP. FOR UHF TV TUNER N-CHANNEL SILICON DUAL-GATE MOS FIELD-EFFECT TRANSISTOR 4 PINS MINI MOLD

#### FEATURES

- Low Noise Figure NF = 2.0 dB TYP. (@ = 900 MHz)
- High Power Gain  $G_{ps} = 17.5 \text{ dB TYP.}$  (@ = 900 MHz)
- Enhancement Typ.
- Suitable for use as RF amplifier in UHF TV tuner.
- Automatically Mounting : Embossed Type Taping
- Small Package : 4 Pins Mini Mold Package. (SC-61)

#### ABSOLUTE MAXIMUM RATINGS (TA = 25 °C)

Drain to Source Voltage	Vdsx	18	V
Gate1 to Source Voltage	Vg1s	±8 (±10)*	V
Gate2 to Source Voltage	Vg2s	±8 (±10)*	V
Gate1 to Drain Voltage	Vg1d	18	V
Gate2 to Drain Voltage	Vg2d	18	V
Drain Current	D	25	mA
Total Power Dissipation	PD	200	mW
Channel Temperature	Tch	125	°C
Storage Temperature	Tstg	-55 to +125	°C
*R∟ ≥ 10 kΩ			



**PRECAUTION**: Avoid high static voltages or electric fields so that this device would not suffer from any damage due to those voltages or fields.


### ELECTRICAL CHARACTERISTICS (TA = 25 °C)

CHARACTERISTIC	SYMBOL	MIN.	TYP.	MAX.	UNIT	TEST CONDITIONS
Drain to Source Breakdown Voltage	BV <sub>DSX</sub>	18			V	$V_{G1S} = V_{G2S} = -2 V$ , ID = 10 $\mu$ A
Drain Current	IDSx	0.01		10.0	mA	Vds = 6 V, Vg2s = 4.5 V, Vg1s = 0.75 V
Gate1 to Source Cutoff Voltage	VG1S(off)	-1.0		+1.0	V	$V_{DS} = 6 V, V_{G2S} = 3 V, I_D = 10 \mu A$
Gate2 to Source Cutoff Voltage	V <sub>G2S(off)</sub>	+0.6	+1.1	+1.6	V	$V_{DS} = 6 V V_{G1S} = 3 V, I_D = 10 \mu A$
Gate1 Reverse Current	IG1SS			±20	nA	$V_{DS} = V_{G2S} = 0 \text{ V},  V_{G1S} = \pm 8 \text{ V}$
Gate2 Reverse Current	Ig2ss			±20	nA	$V_{DS} = V_{G1S} = 0 \text{ V},  V_{G2S} = \pm 8 \text{ V}$
Forward Transfer Admittance	<b>y</b> fs	15	19.5	24	mS	Vps = 6 V, Vg2s = 4.5 V, Ip = 10 mA
						f = 1 kHz
Input Capacitance	Ciss	1.0	1.5	2.0	pF	V <sub>DS</sub> = 6 V, V <sub>G2S</sub> = 4.5 V, I <sub>D</sub> = 10 mA
Output Capacitance	Coss	0.7	1.0	1.3	pF	f = 1 MHz
Reverse Transfer Capacitance	Crss		0.015	0.03	pF	
Power Gain	Gps	14.0	17.5	21.0	dB	Vds = 6 V, Vg2s = 4.5 V, Id = 10 mA
Noise Figure	NF1		2.0	3.0	dB	f = 900 MHz

\_\_\_\_\_


#### IDSX Classification

Rank	U1C	U1D
Marking	U1C	U1D
Ibsx (mA)	0.01 to 4.0	2.0 to 10.0




#### CHARACTERISTICS CURVE (TA = 25 °C)

ID-Drain Current-mA





FORWARD TRANSFER ADMITTANCE vs. GATE1 TO SOURCE VOLTAGE




Vg1s-Gate1 to Source Voltage-V

INPUT CAPACITANCE vs. GATE2 TO SOURCE VOLTAGE





Gps AND NF TEST CIRCUIT AT f = 900 MHz



[MEMO]

[MEMO]

No part of this document may be copied or reproduced in any form or by any means without the prior written consent of NEC Corporation. NEC Corporation assumes no responsibility for any errors which may appear in this document.

NEC Corporation does not assume any liability for infringement of patents, copyrights or other intellectual property rights of third parties by or arising from use of a device described herein or any other liability arising from use of such device. No license, either express, implied or otherwise, is granted under any patents, copyrights or other intellectual property rights of NEC Corporation or others.

While NEC Corporation has been making continuous effort to enhance the reliability of its semiconductor devices, the possibility of defects cannot be eliminated entirely. To minimize risks of damage or injury to persons or property arising from a defect in an NEC semiconductor device, customers must incorporate sufficient safety measures in its design, such as redundancy, fire-containment, and anti-failure features.

NEC devices are classified into the following three quality grades:

"Standard", "Special", and "Specific". The Specific quality grade applies only to devices developed based on a customer designated "quality assurance program" for a specific application. The recommended applications of a device depend on its quality grade, as indicated below. Customers must check the quality grade of each device before using it in a particular application.

Standard: Computers, office equipment, communications equipment, test and measurement equipment, audio and visual equipment, home electronic appliances, machine tools, personal electronic equipment and industrial robots

Special: Transportation equipment (automobiles, trains, ships, etc.), traffic control systems, anti-disaster systems, anti-crime systems, safety equipment and medical equipment (not specifically designed for life support)

Specific: Aircrafts, aerospace equipment, submersible repeaters, nuclear reactor control systems, life support systems or medical equipment for life support, etc.

The quality grade of NEC devices is "Standard" unless otherwise specified in NEC's Data Sheets or Data Books. If customers intend to use NEC devices for applications other than those specified for Standard quality grade, they should contact an NEC sales representative in advance.

Anti-radioactive design is not implemented in this product.

M4 96.5